

Many-Help-One Problem for Gaussian Sources with a Tree Structure on Their Correlation

Yasutada Oohama

Abstract—In this paper we consider the separate coding problem for $L + 1$ correlated Gaussian memoryless sources. We deal with the case where L separately encoded data of sources work as side information at the decoder for the reconstruction of the remaining source. The determination problem of the rate distortion region for this system is the so called many-help-one problem and has been known as a highly challenging problem. The author determined the rate distortion region in the case where the L sources working as partial side information are conditionally independent if the remaining source we wish to reconstruct is given. This condition on the correlation is called the CI condition. In this paper we extend the author's previous result to the case where $L + 1$ sources satisfy a kind of tree structure on their correlation. We call this tree structure of information sources the TS condition, which contains the CI condition as a special case. In this paper we derive an explicit outer bound of the rate distortion region when information sources satisfy the TS condition. We further derive an explicit sufficient condition for this outer bound to be tight. In particular, we determine the sum rate part of the rate distortion region for the case where information sources satisfy the TS condition. For some class of Gaussian sources with the TS condition we derive an explicit recursive formula of this sum rate part.

Index Terms—Multiterminal source coding, many-help-one problem, Gaussian, rate-distortion region, CEO problem.

I. INTRODUCTION

In multi-user source networks separate coding systems of correlated information sources are significant from both theoretical and practical point of view. The first fundamental result on those coding systems was obtained by Slepian and Wolf [1]. They considered a separate source coding system of two correlated information sources. Those two sources are separately encoded and sent to a single destination, where the decoder reconstruct the original sources.

In the above source coding system, we can consider the situation, where the decoder wishes to reproduce one of two sources. We call this source the *primary source*. In this case the remaining source that we call the *auxiliary source* works as a partial side information at the decoder for the reconstruction of the primary source. Wyner [2], Ahlswede and Körner [3] determined the admissible rate region for this system, the set that consists of a pair of transmission rates for which the primary source can be decoded with an arbitrary small error probability.

We can naturally extend the system studied by Wyner, Ahlswede and Körner to the one where there are several separately encoded data of auxiliary sources serving as side

informations at the decoder. The determination of the admissible rate region for this system is called the many-help-one problem. In this sense Wyner, Ahlswede and Körner solved the so called one-helps-one problem. The many-help-one problem has been known as a highly challenging problem. To date, partial solutions given by Körner and Marton [4], Gelfand and Pinsker [5], Oohama [8],[10], and Tavildar *et al.* [11] are known.

Gelfand and Pinsker [5] studied an interesting case of the many-help-one problem. They determined the admissible rate region in the case, where the auxiliary sources are *conditionally independent* if the primary source is given. We hereafter say the above correlation condition on the information sources the CI condition.

In Oohama [8], the author extended the many-help-one problem studied by Gelfand and Pinsker [5] to a continuous case. He considered the many-help-one problem for $L + 1$ correlated memoryless Gaussian sources, where L auxiliary sources work as partial side information at the decoder for the reconstruction of the primary source. The mean square error was adopted as a distortion criterion between the decoded output and the original primary source output. The rate distortion region was defined by the set of all transmission rates for which the average distortion can be upper bounded by a prescribed level. In [8], the author determined the rate distortion region when information sources satisfy the CI condition. This result contains the author's previous works for Gaussian one-helps-one problem [6] and Gaussian CEO problem [7].

The problem still remains open for Gaussian sources with general correlation. Pandya *et al.* [9] studied the general case and derived an outer bound of the rate distortion region using some variant of bounding technique the author [6] used to prove the converse coding theorem for Gaussian one-helps-one problem. However, their bounding method was not sufficient to provide a tight result.

In Oohama [10], the author extended the result of [8]. He considered a case of correlation on Gaussian sources, where $L + 1$ sources satisfy a kind of tree structure on their correlation. The author called this tree structure of information sources the TS condition. The TS condition contains the CI condition as a special case. In [10], the author derived an explicit outer bound of the rate distortion region for Gaussian sources satisfying TS condition. Furthermore, he had shown that for $L = 2$, this outer bound coincides with the rate distortion region. The author also presented a sufficient condition for the outer bound to coincide with the rate distortion region.

Subsequently, Tavildar *et al.* [11] extended the TS condition to a binary Gauss Markov tree structure condition. They

studied a characterization of the rate distortion region for Gaussian source with the complete binary tree structure and succeeded in it. To derive their result, they made the full use of the complete binary tree structure of the source. They further determined the rate distortion region for Gaussian sources with general tree structure.

In Oohama [10], the analysis for matching condition of the rate distortion region and the derived outer bound was not sufficient, so that the author could not realize that there exists a part of the rate distortion region where the outer bound derived by him coincides with the rate distortion region. In this paper we give a further analysis on matching condition for the outer bound derived by Oohama [10] to coincide with the rate distortion region and derive a condition much stronger than the matching condition in [10]. Through this analysis we obtain an insight on a way of examining the sum rate part of the rate distortion region to show that for Gaussian sources with the TS condition the minimum sum rate part of the outer bound given by Oohama [10] is tight. This result implies that in Oohama [10], the author had already obtained an explicit characterization of the sum rate part of the rate distortion region before the work by Tavildar *et al.* [11]. On this optimal sum rate we derive its explicit recursive formula for some class of Gaussian sources with the TS condition. Our formula contains the result of Oohama [7] for Gaussian CEO problem as a special case.

The rest of this paper is organized as follows.

In Section II, we present a problem formulation and state the previous works.

In Section III, we give our main result. We first derive an explicit outer bound of the rate distortion region when information sources satisfy the TS condition. This outer bound is essentially the same as the author's previous outer bound in [10], but it has a form more suitable than the previous one for analysis of a matching condition. Using the derived outer bound, we presented an explicit sufficient condition for the outer bound to coincide with the inner bound.

In Section IV, we investigate the sum rate part of the rate distortion region. We show that for the outer bound in this paper and that in [10], their sum rate parts coincide with the sum rate part of the inner bound. Hence, in the case where information sources satisfy the TS condition, we establish an explicit characterization of the sum rate part of the rate distortion region. This optimal sum rate has a form of optimization problem. For some class of the Gaussian source with the TS condition, we solve this optimization problem to establish an explicit recursive formula of the optimal sum rate.

In Section V, we give the proofs of the results. Finally, in Section VI, we conclude the paper.

II. PROBLEM STATEMENT AND PREVIOUS RESULTS

In this section we state the problem formulation and previous results. We first state some notations used throughout this paper. Let $\Phi = \{1, 2, \dots, |\Phi|\}$ and $\mathcal{A}_i, i \in \Phi$ be arbitrary sets. Consider a random variable $A_i, i \in \Phi$ taking values in $\mathcal{A}_i$. We write n direct product of $\mathcal{A}_i$ as $\mathcal{A}_i^n \triangleq \underbrace{\mathcal{A}_i \times \dots \times \mathcal{A}_i}_n$.




Fig. 1. Communication system with L side informations at the decoder.

Let a random vector consisting of n independent copies of the random variable A_i be denoted by $\mathbf{A}_i = A_{i,1}A_{i,2} \dots A_{i,n}$. We write an element of $\mathcal{A}_i^n$ as $\mathbf{a}_i = a_{i,1}a_{i,2} \dots a_{i,n}$. Let S be an arbitrary subset of Φ . Let $\mathbf{A}_S$ and $\mathbf{A}_S$ denote random vectors $(A_i)_{i \in S}$ and $(\mathbf{A}_i)_{i \in S}$, respectively. Similarly, let $\mathbf{a}_S$ denote a vector $(a_i)_{i \in S}$. When $S = \{k, k+1, \dots, l\}$, we also use the notation $\mathbf{A}_k^l$ for $\mathbf{A}_S$ and use similar notations for other vectors or random variables. When $k = 1$, we sometimes omit subscript 1. Throughout this paper all logarithms are taken to the natural.

A. Formal Statement of the Problem

Let $X_i, i = 0, 1, 2, \dots, L$ be correlated zero mean Gaussian random variables taking values in real lines $\mathcal{X}_i$. Let $\Lambda = \{1, 2, \dots, L\}$. The CI condition Oohama [8] treated corresponds to the case where $X_1, X_2, \dots, X_L$ are independent if X_0 is given. In this paper we deal with the case where $X_1, \dots, X_L$ have some correlation when X_0 is given. Let $\{(X_{0,t}, X_{1,t}, \dots, X_{L,t})\}_{t=1}^\infty$ be a stationary memoryless multiple Gaussian source. For each $t = 1, 2, \dots$, $(X_{0,t}, X_{1,t}, \dots, X_{L,t})$ obeys the same distribution as $(X_0, X_1, \dots, X_L)$.

The multiterminal source coding system treated in this paper is depicted in Fig. 1. For each $i = 0, 1, \dots, L$, the data sequence $\mathbf{X}_i$ is separately encoded to $\varphi_i(\mathbf{X}_i)$ by encoder function φ_i . The encoded data $\varphi_i(\mathbf{X}_i), i = 0, 1, \dots, L$ are sent to the information processing center, where the decoder observes them and outputs the estimation $\hat{\mathbf{X}}_0$ of $\mathbf{X}_0$ by using the decoder function ψ . The encoder functions $\varphi_i, i = 0, 1, \dots, L$ are defined by

$$\varphi_i : \mathcal{X}_i^n \rightarrow \mathcal{M}_i = \{1, 2, \dots, M_i\} \quad (1)$$

and satisfy rate constraints

$$\frac{1}{n} \log M_i \leq R_i + \delta \quad (2)$$

where δ is an arbitrary prescribed positive number. The decoder function ψ is defined by

$$\psi : \mathcal{M}_0 \times \mathcal{M}_1 \times \dots \times \mathcal{M}_L \rightarrow \mathcal{X}_0^n. \quad (3)$$

Denote by $\mathcal{F}_\delta^{(n)}(R_0, R_1, \dots, R_L)$ the set that consists of all the $(L+2)$ tuple of encoder and decoder functions $(\varphi_0, \varphi_1, \dots, \varphi_L, \psi)$ satisfying (1)-(3). Let $d(x, \hat{x}) = (x - \hat{x})^2$, $(x, \hat{x}) \in \mathcal{X}_0^2$ be a square distortion measure. For $\mathbf{X}_0$ and its

estimation $\hat{\mathbf{X}}_0 = \psi(\varphi_0(\mathbf{X}_0), \varphi_1(\mathbf{X}_1), \dots, \varphi_L(\mathbf{X}_L))$, define the average distortion by

$$\Delta(\mathbf{X}_0, \hat{\mathbf{X}}_0) \triangleq \frac{1}{n} \sum_{t=1}^n \text{Ed}(X_{0,t}, \hat{X}_{0,t}).$$

For a given $D > 0$, the rate vector $(R_0, R_1, \dots, R_L)$ is *admissible* if for any positive $\delta > 0$ and any n with $n \geq n_0(\delta)$, there exists $(\varphi_0, \varphi_1, \dots, \varphi_L, \psi) \in \mathcal{F}_\delta^{(n)}(R_0, R_1, \dots, R_L)$ such that $\Delta(\mathbf{X}_0, \hat{\mathbf{X}}_0) \leq D + \delta$. Let $\mathcal{R}_L(D)$ denote the set of all the admissible rate vector. Our aim is to characterize $\mathcal{R}_L(D)$ in an explicit form. On a form of $\mathcal{R}_L(D)$, we have a particular interest in its sum rate part. To examine this quantity, define

$$R_{\text{sum},L}(D, R_0) \triangleq \min_{(R_0, R_1, \dots, R_L) \in \mathcal{R}_L(D)} \left\{ \sum_{i=1}^L R_i \right\}.$$

To determine $R_{\text{sum},L}(D, R_0)$ in an explicit form is also of our interest.

By the rate-distortion theory for single Gaussian sources, when $R_0 \geq \frac{1}{2} \log^+ [\frac{\sigma_{X_0}^2}{D}]$, $R_1 = R_2 = \dots = R_L = 0$ is admissible. Here $\log^+ a = \max\{\log a, 0\}$. Hence, we have

$$\begin{aligned} \mathcal{R}_L(D) \cap \left\{ R_0 \geq \frac{1}{2} \log^+ \left[\frac{\sigma_{X_0}^2}{D} \right] \right\} \\ = \{ (R_0, R_1, \dots, R_L) : R_0 \geq \frac{1}{2} \log^+ \left[\frac{\sigma_{X_0}^2}{D} \right], \\ R_i \geq 0, i \in \Lambda \}. \end{aligned}$$

Throughout this paper we assume that $D \leq \sigma_{X_0}^2$ and $R_0 < \frac{1}{2} \log^+ [\frac{\sigma_{X_0}^2}{D}]$.

B. Tree Structure of Gaussian Sources

In this subsection we explain the tree structure of Gaussian source which is an important class of correlation. Consider the case where the $L+1$ random variables $X_0, X_1, \dots, X_L$ satisfy the following correlations:

$$\left. \begin{aligned} Y_0 &= X_0, \\ Y_i &= Y_{i-1} + Z_i, 1 \leq i \leq L, \\ X_i &= Y_i + N_i, 1 \leq i \leq L-1, \\ X_L &= Y_L, N_L = Z_L, \end{aligned} \right\} \quad (4)$$

where $Z_i, i \in \Lambda$ are L independent Gaussian random variables with mean 0 and variance $\sigma_{Z_i}^2$ and $N_i, i = 1, 2, \dots, L-1$ are $L-1$ independent Gaussian random variables with mean 0 and variance $\sigma_{N_i}^2$. We assume that Z^L is independent of X_0 and that N^{L-1} is independent of X_0 and Z^L . We can see that the above $(X_0, X_1, \dots, X_L)$ has a kind of tree structure (TS). We say that the source $(X_0, X_1, \dots, X_L)$ satisfies the TS condition when it satisfies (4). The TS condition contains the CI condition as a special case by letting $\sigma_{Z_i}, i = 1, 2, \dots, L-1$ be zero. Let S be an arbitrary subset of Λ . The TS condition is equivalent to the condition that for $S \subseteq \Lambda$, the random variables $X_S, (X_0, Z^{L-1}), X_{S^c}$ form Markov chains $X_S \rightarrow (X_0, Z^{L-1}) \rightarrow X_{S^c}$ in this order. The TS and CI conditions in the case of $L = 4$ are shown in Fig. 2 and 3, respectively.




Fig. 2. TS condition in the case of $L = 4$.




Fig. 3. CI condition in the case of $L = 4$.

C. Previous Results

In this subsection we state the previous results on the determination problem of $\mathcal{R}_L(D)$. Let $U_i, i = 0, 1, \dots, L$ be random variables taking values in real lines $\mathcal{U}_i$. For $S \subseteq \Lambda$, define

$$\begin{aligned} \mathcal{G}(D) \triangleq \{ (U_0, U^L) : (U_0, U^L) \text{ is a Gaussian random} \\ \text{vector that satisfies} \\ U^L \rightarrow X^L \rightarrow X_0 \rightarrow U_0 \\ U_S \rightarrow X_{S \cup \{0\}} \rightarrow X_{S^c} \rightarrow U_{S^c} \\ \text{for any } S \subseteq \Lambda \text{ and } \mathbb{E}[X_0 - \tilde{\psi}(U_0, U^L)]^2 \leq D \\ \text{for some linear mapping } \tilde{\psi} : \mathcal{U}_0 \times \mathcal{U}^L \rightarrow \mathcal{X}_0. \} \end{aligned}$$

where $S^c \triangleq \Lambda - S$. Let

$$\pi = \begin{pmatrix} 1 & \dots & i & \dots & L \\ \pi(1) & \dots & \pi(i) & \dots & \pi(L) \end{pmatrix}$$

be an arbitrary permutation on Λ and Π be a set of all permutations on Λ . For $S \subseteq \Lambda$, we set $\pi(S) \triangleq \{\pi(i)\}_{i \in S}$. Define L subsets $S_i, i = 1, 2, \dots, L$ of Λ by $S_i \triangleq \{i, i+1, \dots, L\}$. Set

$$\begin{aligned} \tilde{\mathcal{R}}_{\pi,L}(D) \triangleq \{ (R_0, R_1, \dots, R_L) : \text{There exists a random} \\ \text{vector } (U_0, U^L) \in \mathcal{G}(D) \text{ such that} \\ R_0 \geq I(X_0; U_0 | U^L) \\ R_{\pi(i)} \geq I(X_{\pi(i)}; U_{\pi(i)} | U_{\pi(S_i^c)}) \\ \text{for } i = 1, 2, \dots, L \} \end{aligned}$$

$$\tilde{\mathcal{R}}_L^{(\text{in})}(D) \triangleq \text{conv} \left\{ \bigcup_{\pi \in \Pi} \tilde{\mathcal{R}}_{\pi, L}^{(\text{in})}(D) \right\},$$

where $\text{conv}\{A\}$ denotes a convex hull of the set A . Then, we have the following.

Theorem 1 (Oohama [8]): For Gaussian sources with general correlation

$$\tilde{\mathcal{R}}_L^{(\text{in})}(D) \subseteq \mathcal{R}_L(D).$$

For Gaussian sources with the CI condition the inner bound $\tilde{\mathcal{R}}_L^{(\text{in})}(D)$ is tight, that is

$$\tilde{\mathcal{R}}_L^{(\text{in})}(D) = \mathcal{R}_L(D).$$

The above inner bound $\tilde{\mathcal{R}}_L^{(\text{in})}(D)$ can be regarded as a variant of the inner bound which is well known as the inner bound of Berger [12] and Tung [13]. Theorem 1 contains the solution that Oohama [6] obtained to the one-helps-one problem for Gaussian sources as a special case. When $R_0 = 0$, the second result of Theorem 1 has some implications for the Gaussian CEO problem studied by Viswanathan and Berger [14] and Oohama [7] and source coding problem for multiterminal communication systems with a remote source investigated by Yamamoto and Itoh [15] and Flynn and Gray [16].

The notion of TS condition for Gaussian sources was first introduced by Oohama [10]. Tavildar *et al.* [11] extended the TS condition to a binary Gauss Markov tree structure condition. They studied a full characterization of the rate distortion region for Gaussian sources with a binary tree structure. In the next section we shall state the results of Tavildar *et al.* [11] and compare them with our results.

III. RESULTS ON THE RATE DISTORTION REGION

In this section, we state our main results on inner and outer bounds of $\mathcal{R}_L(D)$ in the case where $(X_0, X_1, \dots, X_L)$ satisfies the TS condition.

A. Definition of Functions and their Properties

In this subsection we define several functions which are necessary to describe our results and present their properties. Let $r_i, i \in \Lambda$ be nonnegative numbers. Define the sequence of nonnegative functions $\{f_l(r^L)\}_{l=1}^{L-1} \cup \{f_0(r^L)\}$ by the following recursion:

$$\left. \begin{aligned} f_{L-1}(r_{L-1}^L) &= \frac{1-e^{-2r_{L-1}}}{\sigma_{N_{L-1}}^2} + \frac{1-e^{-2r_L}}{\sigma_{N_L}^2}, \\ f_l(r_l^L) &= \frac{f_{l+1}(r_{l+1}^L)}{1+\sigma_{Z_{l+1}}^2 f_{l+1}(r_{l+1}^L)} + \frac{1-e^{-2r_l}}{\sigma_{N_l}^2}, \\ L-2 \geq l \geq 1, \\ f_0(r^L) &= \frac{f_1(r^L)}{1+\sigma_{Z_1}^2 f_1(r^L)}. \end{aligned} \right\} \quad (5)$$

Next, we define the sequence of nonnegative functions

$$\{g_l(D, r_0)\}_{l=0,1} \cup \{g_l(D, r_0, r^{l-1})\}_{l=2}^{L-1}$$

by the following recursion:

$$\left. \begin{aligned} g_0(D, r_0) &= \frac{e^{-2r_0}}{D} - \frac{1}{\sigma_{X_0}^2}, \\ g_1(D, r_0) &= \frac{g_0(D, r_0)}{1-\sigma_{Z_1}^2 g_0(D, r_0)}, \\ g_{l+1}(D, r_0, r^l) &= \frac{\left[g_l(D, r_0, r^{l-1}) - \frac{1}{\sigma_{N_l}^2} (1-e^{-2r_l}) \right]^+}{1-\sigma_{Z_{l+1}}^2 \left[g_l(D, r_0, r^{l-1}) - \frac{1}{\sigma_{N_l}^2} (1-e^{-2r_l}) \right]^+}, \\ 1 \leq l \leq L-2, \end{aligned} \right\} \quad (6)$$

where $[a]^+ = \max\{a, 0\}$. Let $\mathcal{B}_L(D)$ be the set of all nonnegative vectors r_0^L that satisfy

$$f_0(r^L) \geq g_0(D, r_0) = \frac{e^{-2r_0}}{D} - \frac{1}{\sigma_{X_0}^2}.$$

Let $\partial\mathcal{B}_L(D)$ be the boundary of $\mathcal{B}_L(D)$, that is, the set of all nonnegative vectors r_0^L that satisfy

$$f_0(r^L) = g_0(D, r_0) = \frac{e^{-2r_0}}{D} - \frac{1}{\sigma_{X_0}^2}.$$

We can easily show that the functions we have defined satisfy the following property.

Property 1:

- a) For each $i \in \Lambda$, $f_0(r^L)$ is a monotone increasing function of r_i . For each $1 \leq l \leq L$ and for each $i = l, l+1, \dots, L$, $f_l(r_l^L)$ is a monotone increasing function of r_i .
- b) For each $2 \leq l \leq L-1$ and for each $i = 0, 1, \dots, l-1$, $g_l(D, r_0, r^{l-1})$ is a monotone decreasing function of r_i .
- c) If $r_0^L \in \mathcal{B}_L(D)$, then, for $0 \leq l \leq L-1$,

$$g_l(D, r_0, r^{l-1}) \leq f_l(r_l^L).$$

In the above L inequalities the equalities simultaneously hold if and only if $r_0^L \in \partial\mathcal{B}_L(D)$.

Define

$$\begin{aligned} F(r^L) &\triangleq \prod_{l=1}^{L-1} [1 + \sigma_{Z_l}^2 f_l(r_l^L)], \\ G(D, r_0, r^{L-2}) &\triangleq \prod_{l=1}^{L-1} [1 + \sigma_{Z_l}^2 g_l(D, r_0, r^{l-1})]. \end{aligned}$$

For $S \subseteq \Lambda$, define

$$f_0(r_S) \triangleq f_0(r^L)|_{r_{S^c}=\mathbf{0}}, \quad F(r_S) \triangleq F(r^L)|_{r_{S^c}=\mathbf{0}}.$$

We can easily show that the functions $F(r^L)$ and $G(D, r_0, r^{L-2})$ satisfy the following property.

Property 2:

- a) For each $i \in S$, $F(r_S)$ is a monotone increasing function of r_i .
- b) For each $i = 0, 1, \dots, L-2$, $G(D, r_0, r^{L-2})$ is a monotone decreasing function of r_i .
- c) If $r_0^L \in \mathcal{B}_L(D)$, then

$$G(D, r_0, r^{L-2}) \leq F(r^L).$$

The equality holds if and only if $r_0^L \in \partial\mathcal{B}_L(D)$.

For $D > 0, r_i \geq 0, i \in \Lambda$ and $S \subseteq \Lambda$, define

$$\begin{aligned} & J_S(D, r_0, r^{L-2}, r_S | r_{S^c}) \\ & \triangleq \frac{1}{2} \log^+ \left[\frac{G(D, r_0, r^{L-2})}{F(r_{S^c})} \cdot \frac{\sigma_{X_0}^2 e^{-2r_0}}{\{1 + \sigma_{X_0}^2 f_0(r_{S^c})\} D} \cdot \prod_{i \in S} e^{2r_i} \right], \\ & K_S(r_S | r_{S^c}) \\ & \triangleq \frac{1}{2} \log \left[\frac{F(r^L)}{F(r_{S^c})} \cdot \frac{1 + \sigma_{X_0}^2 f_0(r^L)}{1 + \sigma_{X_0}^2 f_0(r_{S^c})} \cdot \prod_{i \in S} e^{2r_i} \right]. \end{aligned}$$

We can show that for $S \subseteq \Lambda$, $K_S(r_S | r_{S^c})$ and $J_S(D, r_0, r^{L-2}, r_S | r_{S^c})$ satisfy the following two properties.

Property 3:

a) If $r_0^L \in \mathcal{B}_L(D)$, then, for any $S \subseteq \Lambda$,

$$J_S(D, r_0, r^{L-2}, r_S | r_{S^c}) \leq K_S(r_S | r_{S^c}).$$

The equality holds when $r_0^L \in \partial \mathcal{B}_L(D)$.

b) Suppose that $r^L \in \mathcal{B}_L(D)$. If $r^L|_{r_S=0}$ still belongs to $\mathcal{B}_L(D)$, then,

$$J_S(D, r_0, r^{L-2}, r_S | r_{S^c})|_{r_S=0} = K_S(r_S | r_{S^c})|_{r_S=0} = 0.$$

Property 4: Fix $r^L \in \mathcal{B}_L(D)$. For $S \subseteq \Lambda$, set

$$\rho_S = \rho_S(r_S | r_{S^c}) \triangleq J_S(D, r_0, r^{L-2}, r_S | r_{S^c}).$$

By definition it is obvious that $\rho_S, S \subseteq \Lambda$ are nonnegative. We can show that $\rho \triangleq \{\rho_S\}_{S \subseteq \Lambda}$ satisfies the followings:

- a) $\rho_\emptyset = 0$.
- b) $\rho_A \leq \rho_B$ for $A \subseteq B \subseteq \Lambda$.
- c) $\rho_A + \rho_B \leq \rho_{A \cap B} + \rho_{A \cup B}$.

In general (Λ, ρ) is called a *co-polymatroid* if the nonnegative function ρ on 2^Λ satisfies the above three properties. Similarly, we set

$$\tilde{\rho}_S = \tilde{\rho}_S(r_S | r_{S^c}) \triangleq K_S(r_S | r_{S^c}), \quad \tilde{\rho} = \{\tilde{\rho}_S\}_{S \subseteq \Lambda}.$$

Then, $(\Lambda, \tilde{\rho})$ also has the same three properties as those of (Λ, ρ) and becomes a co-polymatroid.

B. Results

In this subsection we present our results on inner and outer bounds of $\mathcal{R}_L(D)$. In the previous work [10], we derived an outer bound of $\mathcal{R}_L(D)$. We denote this outer bound by

$\hat{\mathcal{R}}_L^{(\text{out})}(D)$. According to [10], $\hat{\mathcal{R}}_L^{(\text{out})}(D)$ is given by

$$\begin{aligned} & \hat{\mathcal{R}}_L^{(\text{out})}(D) \\ & = \left\{ (R_0, R^L) : \text{There exists a nonnegative vector} \right. \\ & \quad (r_0, r^L) \text{ such that} \\ & \quad R_0 \geq r_0 \geq \frac{1}{2} \log^+ \left[\frac{\sigma_{X_0}^2}{\{1 + \sigma_{X_0}^2 f_0(r^L)\} D} \right], \\ & \quad R_i \geq r_i \text{ for any } i \in \Lambda, \\ & \quad R_0 + \sum_{i \in S} R_i \\ & \quad \geq \frac{1}{2} \log^+ \left[\frac{G(D, r_0, r^{L-2}) \sigma_{X_0}^2}{F(r_{S^c}) \{1 + \sigma_{X_0}^2 f_0(r_{S^c})\} D} \right] \\ & \quad + \sum_{i=1}^L r_i \\ & \quad \left. \text{for any } S \subseteq \Lambda \right\}. \end{aligned}$$

Set

$$\begin{aligned} \mathcal{R}_L^{(\text{out})}(D, r_0^L) & \triangleq \{ (R_0, R_1, \dots, R_L) : \\ & \quad R_0 \geq r_0, \\ & \quad \sum_{i \in S} R_i \geq J_S(D, r_0, r^{L-2}, r_S | r_{S^c}), \\ & \quad \text{for any } S \subseteq \Lambda \} , \\ \mathcal{R}_L^{(\text{in})}(r_0^L) & \triangleq \{ (R_0, R_1, \dots, R_L) : \\ & \quad R_0 \geq r_0, \\ & \quad \sum_{i \in S} R_i \geq K_S(r_S | r_{S^c}), \\ & \quad \text{for any } S \subseteq \Lambda \} , \\ \mathcal{R}_L^{(\text{out})}(D) & \triangleq \bigcup_{r_0^L \in \mathcal{B}_L(D)} \mathcal{R}_L^{(\text{out})}(D, r_0^L), \\ \mathcal{R}_L^{(\text{in})}(D) & \triangleq \bigcup_{r_0^L \in \mathcal{B}_L(D)} \mathcal{R}_L^{(\text{in})}(r_0^L). \end{aligned}$$

Our main result is as follows.

Theorem 2: For Gaussian sources with the TS condition

$$\begin{aligned} \mathcal{R}_L^{(\text{in})}(D) & \subseteq \tilde{\mathcal{R}}_L^{(\text{in})}(D) \subseteq \mathcal{R}_L(D) \\ & \subseteq \hat{\mathcal{R}}_L^{(\text{out})}(D) \subseteq \mathcal{R}_L^{(\text{out})}(D). \end{aligned}$$

Proof of this theorem will be given in Section V. The inclusion $\mathcal{R}_L(D) \subseteq \hat{\mathcal{R}}_L^{(\text{out})}(D)$ and an outline of proof of this inclusion was given in Oohama [10]. Furthermore, by Theorem 1, we have $\tilde{\mathcal{R}}_L^{(\text{in})}(D) \subseteq \mathcal{R}_L(D)$. Hence, it suffices to show $\hat{\mathcal{R}}_L^{(\text{out})}(D) \subseteq \mathcal{R}_L^{(\text{out})}(D)$ and $\mathcal{R}_L^{(\text{in})}(D) \subseteq \tilde{\mathcal{R}}_L^{(\text{in})}(D)$ to prove Theorem 2. Proofs of those two inclusions will be given in Section V. We can directly prove $\mathcal{R}_L(D) \subseteq \mathcal{R}_L^{(\text{out})}(D)$ in a manner similar to that of Oohama [10]. For the detail of the direct proof of $\mathcal{R}_L(D) \subseteq \mathcal{R}_L^{(\text{out})}(D)$, see Appendix B.

An essential difference between $\mathcal{R}_L^{(\text{out})}(D)$ and $\mathcal{R}_L^{(\text{in})}(D)$ is the difference between $J_S(D, r_0, r^{L-2}, r_S | r_{S^c})$ in the definition of $\mathcal{R}_L^{(\text{out})}(D)$ and $K_S(r_S | r_{S^c})$ in the definition of $\mathcal{R}_L^{(\text{in})}(D)$. By Property 3 part a) and the definitions of $\mathcal{R}_L^{(\text{out})}(D, r_0^L)$ and $\mathcal{R}_L^{(\text{in})}(r_0^L)$, if $r_0^L \in \partial \mathcal{B}_L(D)$, then,

$$\mathcal{R}_L^{(\text{out})}(D, r_0^L) = \mathcal{R}_L^{(\text{in})}(r_0^L).$$




Fig. 4. TS conditions in the case of $L = 2$ and the case of $L = 3$ and $Z_2 = 0$.

This gap suggests a possibility that in some cases those two bounds match. In the following we present a sufficient condition for $\mathcal{R}_L^{(\text{out})}(D) \subseteq \mathcal{R}_L^{(\text{in})}(D)$. We consider the following condition on $G(D, r_0, r^{L-2})$.

Condition: For each $l = 1, 2, \dots, L-2$, $e^{2r_l} G(D, r_0, r^{L-2})$ is a monotone increasing function of r_l .

We call the above condition the MI condition. The following is our main result on a matching condition on inner and outer bounds.

Lemma 1: For Gaussian sources with the TS condition if $G(D, r_0, r^{L-2})$ satisfies the MI condition, then,

$$\mathcal{R}_L^{(\text{out})}(D) \subseteq \mathcal{R}_L^{(\text{in})}(D).$$

Proof of this lemma is given in Section V. Note that when $L = 2$ or $\sigma_{Z_l} = 0$, for $l = 2, 3, \dots, L-1$ under the TS condition, we have

$$G(D, r_0, r^{L-2}) = 1 + \sigma_{Z_1}^2 g_1(D, r_0),$$

which satisfies the MI condition. TS conditions in the case of $L = 2$ and the case of $L = 3, Z_2 = 0$ is shown in Fig. 4. Note that those two conditions are different from the CI condition. Combining Lemma 1 and Theorem 2, we establish the following.

Theorem 3: For Gaussian sources with the TS condition

$$\mathcal{R}_2^{(\text{in})}(D) = \mathcal{R}_2(D) = \hat{\mathcal{R}}_2^{(\text{out})}(D) = \mathcal{R}_2^{(\text{out})}(D).$$

Furthermore, if $G(D, r_0, r^{L-2})$ satisfies the MI condition, then,

$$\mathcal{R}_L^{(\text{in})}(D) = \mathcal{R}_L(D) = \hat{\mathcal{R}}_L^{(\text{out})}(D) = \mathcal{R}_L^{(\text{out})}(D).$$

In Oohama [10], the equality $\mathcal{R}_2(D) = \hat{\mathcal{R}}_2^{(\text{out})}(D)$ was stated without complete proof. We can see that this equality can be obtained by Theorem 2, Lemma 1, and the fact that the MI condition holds for $L = 2$.

Next, we present a sufficient condition for $G(D, r_0, r^{L-2})$ to satisfy the MI condition. Let $\{f_j^*\}_{j=1}^{L-1}$ be a sequence of positive numbers defined by the following recursion:

$$\left. \begin{aligned} f_{L-1}^* &= \frac{1}{\sigma_{N_{L-1}}^2} + \frac{1}{\sigma_{N_L}^2}, \\ f_l^* &= \frac{f_{l+1}^*}{1 + \sigma_{Z_{l+1}}^2 f_{l+1}^*} + \frac{1}{\sigma_{N_l}^2}, L-2 \geq l \geq 1. \end{aligned} \right\} \quad (7)$$

By definition it is obvious that $f_l(r_l^L) \leq f_l^*$. Then, we have the following proposition.




Fig. 5. TS condition in the case of $L = 3$.

Proposition 1: If

$$\sum_{k=l}^{L-2} \frac{\sigma_{Z_{k+1}}^2}{\sigma_{N_l}^2} \left(1 + \sigma_{Z_{k+1}}^2 f_{k+1}^*\right) \prod_{j=l+1}^k \left(1 + \sigma_{Z_j}^2 f_j^*\right)^2 \leq 1 \quad (8)$$

hold for $l = 1, 2, \dots, L-2$, then, $G(D, r_0, r^{L-2})$ satisfies the MI condition.

Proof of this proposition will be given in Appendix A. It can be seen from this proposition that for $L \geq 3$, the MI condition holds for relatively small values of $\sigma_{Z_l}, l = 2, \dots, L-1$. In particular, when $L = 3$, the sufficient condition given by (8) is

$$\frac{\sigma_{Z_2}^2}{\sigma_{N_1}^2} \left\{ 1 + \sigma_{Z_2}^2 \left(\frac{1}{\sigma_{N_2}^2} + \frac{1}{\sigma_{N_3}^2} \right) \right\} \leq 1.$$

Solving the above inequality with respect to $\sigma_{Z_2}^2$, we have

$$\sigma_{Z_2}^2 \leq \frac{2}{1 + \sqrt{1 + 4\sigma_{N_1}^2 \left(\frac{1}{\sigma_{N_2}^2} + \frac{1}{\sigma_{N_3}^2} \right)}} \cdot \sigma_{N_1}^2.$$

The TS condition in the case of $L = 3$ is shown in Fig. 5.

C. Binary Tree Structure Condition

As a correlation property of Gaussian source Tavildar *et al.* [11] introduced a binary Gauss Markov tree structure condition. They studied a full characterization of the rate distortion region for Gaussian sources with this binary tree structure. In this subsection we describe their result and compare it with our results.

We first explain the binary tree structure introduced by them. Let k be a positive integer. We consider the case where $L = 2^k$. Let $N_i^{(j)}, 1 \leq i \leq 2^j, 1 \leq j \leq k$, be zero mean independent Gaussian random variables with variance $\sigma_{N_i^{(j)}}^2$. Those $2^{k+1} - 2$ random variables are independent of X_0 . Define the sequence of Gaussian random variables $\{Y_i^{(j)}\}_{1 \leq i \leq 2^j, 0 \leq j \leq k}$ by the following recursion:

$$\left. \begin{aligned} Y_1^{(0)} &= X_0, \\ Y_i^{(j)} &= Y_{\lceil \frac{i}{2} \rceil}^{(j-1)} + N_i^{(j)}, \\ &\quad \text{for } 1 \leq i \leq 2^j, 0 \leq j \leq k, \\ X_i &= Y_i^{(k)}, \text{ for } 1 \leq i \leq 2^k, \end{aligned} \right\} \quad (9)$$

where $\lceil a \rceil$ stands for the smallest integer not below a . We say that for $L = 2^k$ the Gaussian source $(X_0, X_1, \dots, X_L)$




Fig. 6. BTS condition in the case of $L = 4$.




Fig. 7. BTS condition in the case of $L = 4$, $\sigma_{N_1^{(2)}} \rightarrow \infty$ and $N_2^{(2)} = 0$ is equivalent to the TS condition in the case of $L = 3$ and $Z_1 = 0$.

satisfies the binary tree structure (BTS) condition when it satisfies (9). The binary tree structure in the case of $k = 2$ and $L = 2^k = 4$ is shown in Fig. 6. In this example, let $\sigma_{N_1^{(2)}} \rightarrow \infty$ and $N_2^{(2)} = 0$. Then, X_1 becomes independent of (X_2, X_3, X_4) and (X_2, X_3, X_4) has the same correlation property as the TS condition in the case of $L = 3$ and $Z_1 = 0$. The BTS condition in this case is shown in Fig. 7. In general the set of Gaussian sources satisfying the TS condition and $Z_1 = 0$ can be embedded into the set of Gaussian sources satisfying BTS condition.

The communication system treated by Tavildar *et al.* is shown in Fig. 8. It can be seen from this figure that their problem set up is slightly different from ours. In their communication system there is no encoder that can directly access to the source $\mathbf{X}_0$. Tavildar *et al.* studied a characterization of the rate distortion region $\mathcal{R}_L(D) \cap \{R_0 = 0\}$ for Gaussian sources with the binary tree structure and succeeded in it. Their result is the following.

Theorem 4 (Tavildar *et al.* [11]): When $L = 2^k$ for some integer k and $(X_0, X_1, \dots, X_L)$ satisfies the BTS condition, we have

$$\mathcal{R}_L(D) \cap \{R_0 = 0\} = \tilde{\mathcal{R}}_L^{(\text{in})}(D) \cap \{R_0 = 0\}.$$

From the above theorem we have the following corollary.

Corollary 1 (Tavildar *et al.* [11]): When $(X_0, X_1, \dots, X_L)$ satisfies the TS condition and $Z_1 = 0$, we have

$$\mathcal{R}_L(D) \cap \{R_0 = 0\} = \tilde{\mathcal{R}}_L^{(\text{in})}(D) \cap \{R_0 = 0\}.$$

The BTS condition differs from the TS condition in its symmetrical property, which plays an essential role in the proof of Theorem 4. We think that the method of Tavildar




Fig. 8. Communication system that Tavildar *et al.* treated.

et al. [11] is applicable to the general case where Z_1 is not constant and $R_0 > 0$ and that $\mathcal{R}_L(D) = \tilde{\mathcal{R}}_L^{(\text{in})}(D)$ still holds in this general case.

Unfortunately, our approach developed in [10] and this paper can not establish $\mathcal{R}_L(D) = \tilde{\mathcal{R}}_L^{(\text{in})}(D)$ for Gaussian sources satisfying the TS condition without requiring the condition on the variances of $Z_i, 2 \leq i \leq L-1$ and $N_i, 1 \leq i \leq L$, specified with (8) in Proposition 1. However, we think that our work in [10] had provided an important step toward the full characterization of the rate distortion region established by Tavildar *et al.* [11].

IV. SUM RATE PART OF THE RATE DISTORTION REGION

In this section we state our result on the rate sum part of $\mathcal{R}_L(D)$. Set

$$R_{\text{sum},L}^{(l)}(D, R_0) \triangleq \min_{\substack{r^L: f_0(r^L) \\ \geq g_0(D, R_0)}} J_\Lambda(D, R_0, r^{L-2}, r^L),$$

$$R_{\text{sum},L}^{(u)}(D, R_0) \triangleq \min_{\substack{r^L: f_0(r^L) \\ \geq g_0(D, R_0)}} K_\Lambda(r^L).$$

Let $\hat{R}_{\text{sum},L}^{(l)}(D, R_0)$ be the minimum sum rate for $\hat{\mathcal{R}}_L^{(\text{out})}(D)$, that is,

$$\hat{R}_{\text{sum},L}^{(l)}(D, R_0) \triangleq \min_{(R_0, R_1, \dots, R_L) \in \hat{\mathcal{R}}_L^{(\text{out})}(D)} \left\{ \sum_{i=1}^L R_i \right\}.$$

Then, it immediately follows from Theorem 2 that we have the following corollary.

Corollary 2: For Gaussian sources with the TS condition

$$R_{\text{sum},L}^{(l)}(D, R_0) \leq \hat{R}_{\text{sum},L}^{(l)}(D, R_0) \\ \leq R_{\text{sum},L}(D, R_0) \leq R_{\text{sum},L}^{(u)}(D, R_0).$$

On the other hand, we have the following lemma.

Lemma 2: For Gaussian sources with the TS condition, we have

$$R_{\text{sum},L}^{(l)}(D, R_0) \geq R_{\text{sum},L}^{(u)}(D, R_0).$$

Proof of this lemma will be given in Section V. Combining Corollary 2 and Lemma 2, we have the following.

Theorem 5: For Gaussian sources with the TS condition

$$\begin{aligned} R_{\text{sum},L}(D, R_0) &= R_{\text{sum},L}^{(\text{u})}(D, R_0) = \hat{R}_{\text{sum},L}^{(1)}(D, R_0) \\ &= R_{\text{sum},L}^{(1)}(D, R_0) \\ &= \min_{\substack{r^L: f_0(r^L) \\ = g_0(D, R_0)}} \left[\sum_{l=1}^L r_l + \frac{1}{2} \log F(r^L) \right] \\ &\quad - R_0 + \frac{1}{2} \log \frac{\sigma_{X_0}^2}{D}. \end{aligned}$$

The optimal sum rate $R_{\text{sum},L}(D, R_0)$ has a form of optimization problem. In the remaining part of this section we deal with this optimization problem. For $1 \leq l \leq L$, set $\sigma_{N_l}^2 = \sigma_l^2$, $\sigma_{Z_l}^2 = \epsilon_l \sigma_l^2$. By the TS condition ϵ_L should be one. For some class of Gaussian source satisfying TS condition, we solve the optimization problem to derive a parametric form of $R_{\text{sum},L}(D, R_0)$. The recursion (5) is

$$\left. \begin{aligned} f_L(r_L) &= \frac{1}{\sigma_L^2} (e^{2r_L} - 1), \\ f_{l-1}(r_{l-1}^L) &= \frac{f_l(r_l^L)}{1 + \epsilon_l \sigma_l^2 f_l(r_l^L)} + \frac{1}{\sigma_{l-1}^2} (1 - e^{-2r_{l-1}}) \\ &\quad \text{for } L \geq l \geq 2, \\ f_0(r^L) &= \frac{f_1(r_1^L)}{1 + \epsilon_1 \sigma_1^2 f_1(r_1^L)}. \end{aligned} \right\} \quad (10)$$

The optimization problem presenting $R_{\text{sum},L}(D, R_0)$ is

$$\begin{aligned} R_{\text{sum},L}(D, R_0) &= \min_{\substack{r^L: f_0(r^L) \\ = g_0(D, R_0)}} \left[\sum_{l=1}^L r_l + \sum_{l=1}^{L-1} \frac{1}{2} \log (1 + \epsilon_l \sigma_l^2 f_l(r_l^L)) \right] \\ &\quad - R_0 + \frac{1}{2} \log \frac{\sigma_{X_0}^2}{D}. \end{aligned}$$

Set

$$\alpha_l \triangleq \frac{\sigma_l^2 f_l(r_l^L)}{1 + \epsilon_l \sigma_l^2 f_l(r_l^L)}, \text{ for } L \geq l \geq 1. \quad (11)$$

By the above transformation, we transform the variable r^L into α^L . From (11), we have

$$f_l = f_l(r_l^L) = \frac{1}{\sigma_l^2} \cdot \frac{\alpha_l}{1 - \epsilon_l \alpha_l}, \text{ for } L \geq l \geq 1. \quad (12)$$

Note that $f_l \geq 0$ for $L \geq l \geq 1$. Then, from (12), α_l , $L \geq l \geq 1$ must satisfy $0 \leq \alpha_l < \epsilon_l^{-1}$. For $L \geq l \geq 2$, set $\tau_l \triangleq \sigma_l^2 / \sigma_{l-1}^2$. From (10) and (12), we have

$$e^{-2r_{l-1}} = 1 - \frac{\alpha_{l-1}}{1 - \epsilon_{l-1} \alpha_{l-1}} + \frac{\alpha_l}{\tau_l}, \text{ for } L \geq l \geq 2. \quad (13)$$

Since $r_{l-1} \geq 0$ for $L \geq l \geq 2$ and (13), α_l , $L \geq l \geq 2$ must satisfy

$$\left. \begin{aligned} 0 \leq \alpha_l &\leq \frac{\tau_l \alpha_{l-1}}{1 - \epsilon_{l-1} \alpha_{l-1}}, \\ \tau_l \left(\frac{\alpha_{l-1}}{1 - \epsilon_{l-1} \alpha_{l-1}} - 1 \right) &< \alpha_l < \epsilon_l^{-1}. \end{aligned} \right\} \quad (14)$$

Let $\prod_{l=1}^L [0, \epsilon_l^{-1})$ be a L direct product of the semi-open intervals $[0, \epsilon_l^{-1})$, $1 \leq l \leq L$. Let $\mathcal{A}_L$ be a set of all L dimensional vectors $\alpha^L \in \prod_{l=1}^L [0, \epsilon_l^{-1})$ that satisfy (14).

Using α^L , $R_{\text{sum},L}(D, R_0)$ is rewritten as

$$\begin{aligned} R_{\text{sum},L}(D, R_0) &= \min_{\substack{\alpha_2^L \in \mathcal{A}_L(\alpha_1), \\ \alpha_1 = \sigma_1^2 g_0(D, R_0)}} \left(-\frac{1}{2} \right) \left[\sum_{l=1}^{L-1} \left\{ \log \left(1 - \frac{\alpha_l}{1 - \epsilon_l \alpha_l} + \frac{\alpha_{l+1}}{\tau_{l+1}} \right) \right. \right. \\ &\quad \left. \left. + \log(1 - \epsilon_l \alpha_l) \right\} + \log(1 - \alpha_L) \right] \\ &\quad - R_0 + \frac{1}{2} \log \frac{\sigma_{X_0}^2}{D}, \end{aligned}$$

where $\mathcal{A}_L(\alpha_1) \triangleq \{\alpha_2^L : \alpha^L = (\alpha_1, \alpha_2^L) \in \mathcal{A}_L\}$. To solve the above optimization problem, set

$$\zeta = \zeta(\alpha_2^L) \triangleq \sum_{l=1}^{L-1} \left\{ \log \left(1 - \frac{\alpha_l}{1 - \epsilon_l \alpha_l} + \frac{\alpha_{l+1}}{\tau_{l+1}} \right) + \log(1 - \epsilon_l \alpha_l) \right\} + \log(1 - \alpha_L).$$

Then, we have the following lemma.

Lemma 3: For $\alpha_2^L \in \mathcal{A}(\alpha_1)$, $\zeta(\alpha_2^L)$ is strictly concave with respect to α_2^L .

Proof of this lemma will be given in Appendix C. It can be seen from this lemma that if we can find θ_2^L satisfying $\nabla \zeta|_{\alpha_2^L = \theta_2^L} = \mathbf{0}$ and $\theta_2^L \in \mathcal{A}_L(\sigma_1^2 g_0(D, R_0))$, this θ_2^L is the unique vector which attains $R_{\text{sum},L}(D, R_0)$. We shall give such θ_2^L in an explicit form of recursion. Let $\omega \in [0, 1)$. Define the sequence of functions $\{\theta_l(\omega)\}_{l=1}^L$ by the following recursion:

$$\left. \begin{aligned} \theta_L(\omega) &= \omega, \\ \theta_{L-1}(\omega) &= \frac{\frac{2\theta_L(\omega)-1}{\tau_L} + 1}{1 + \epsilon_{L-1} \left[\frac{2\theta_L(\omega)-1}{\tau_L} + 1 \right]}, \\ \theta_{l-1}(\omega) &= \frac{\frac{1}{\tau_l} \left[2\theta_l(\omega) - \frac{1 + \frac{\theta_{l+1}(\omega)}{\tau_{l+1}}}{1 + \epsilon_l \left(1 + \frac{\theta_{l+1}(\omega)}{\tau_{l+1}} \right)} + \tau_l \right]}{1 + \frac{\epsilon_{l-1}}{\tau_l} \left[2\theta_l(\omega) - \frac{1 + \frac{\theta_{l+1}(\omega)}{\tau_{l+1}}}{1 + \epsilon_l \left(1 + \frac{\theta_{l+1}(\omega)}{\tau_{l+1}} \right)} + \tau_l \right]} \end{aligned} \right\} \quad (15)$$

for $L-1 \geq l \geq 2$.

Then, we have the following lemma.

Lemma 4: The sequence of functions $\{\theta_l(\omega)\}_{l=1}^L$ defined by (15) satisfies the followings.

a) Suppose that $\tau_l = \sigma_l^2 / \sigma_{l-1}^2$, $L \geq l \geq 2$ satisfy the following condition.

$$\left. \begin{aligned} \tau_L &\geq 1, \text{ for } l = L, \\ \tau_l &\geq \frac{1}{1 + \epsilon_l}, \text{ for } L-1 \geq l \geq 2. \end{aligned} \right\} \quad (16)$$

Then, for $L \geq l \geq 2$, we have the following.

$$\left. \begin{aligned} 0 \leq \theta_l(\omega) &\leq \frac{\tau_l \theta_{l-1}(\omega)}{1 - \epsilon_{l-1} \theta_{l-1}(\omega)}, \\ \tau_l \left(\frac{\theta_{l-1}(\omega)}{1 - \epsilon_{l-1} \theta_{l-1}(\omega)} - 1 \right) &< \theta_l(\omega) < \epsilon_l^{-1}. \end{aligned} \right\} \quad (17)$$

The above (17) imply that $\theta_2^L(\omega) \in \mathcal{A}_L(\theta_1(\omega))$.

b)

$$\nabla \zeta|_{\alpha_2^L = \theta_2^L(\omega)} = \mathbf{0}.$$

c) For each $L - 1 \geq l \geq 1$, $\theta_l(\omega)$ is differentiable with respect to $\omega \in [0, 1]$ and satisfies the following:

$$\begin{aligned} \frac{d\theta_l}{d\omega} &\geq \left[\frac{2(L-l)}{\left\{1 + \epsilon_{L-1} \left(\frac{2\omega-1}{\tau_L} + 1 \right)\right\}^2} - \frac{L-(l+1)}{\left\{1 + \epsilon_{L-1} \left(\frac{\omega}{\tau_L} + 1 \right)\right\}^2} \right] \\ &\quad \times \frac{\sigma_l^2}{\sigma_L^2} \cdot \prod_{j=l+1}^{L-1} \frac{1}{\left\{1 + \epsilon_{j-1} \left(\frac{\theta_j(\omega)}{\tau_j} + 1 \right)\right\}^2} \\ &\geq (L-l+1) \cdot \frac{\sigma_l^2}{\sigma_L^2} \cdot \prod_{j=l+1}^L \frac{1}{\left\{1 + \epsilon_{j-1} \left(\frac{\theta_j(\omega)}{\tau_j} + 1 \right)\right\}^2} \\ &> 0. \end{aligned}$$

This implies that for each $1 \leq l \leq L$, the mapping $\omega \in [0, 1] \mapsto \theta_l(\omega)$ is an injection.

Proof of this lemma is given in Appendix D. From this lemma, we obtain the following theorem.

Theorem 6: Let $\{\theta_l(\omega)\}_{l=1}^L$ be a sequence of functions defined by (15). Suppose that the Gaussian source satisfies the TS condition and the condition (16) stated in Lemma 4. Then, we have the following parametric form of $R_{\text{sum},L}(D, R_0)$ with the parameter $\omega \in [0, 1]$:

$$\begin{aligned} \sigma_1^2 g_0(D, R_0) &= \sigma_1^2 \left[\frac{e^{-2R_0}}{D} - \frac{1}{\sigma_{X_0}^2} \right] = \theta_1(\omega), \\ R_{\text{sum},L}(D, R_0) &= \left(-\frac{1}{2} \right) \left[\sum_{l=1}^{L-1} \left\{ \log \left(1 - \frac{\theta_l(\omega)}{1 - \epsilon_l \theta_l(\omega)} + \frac{\theta_{l+1}(\omega)}{\tau_{l+1}} \right) \right. \right. \\ &\quad \left. \left. + \log(1 - \epsilon_l \theta_l(\omega)) \right\} + \log(1 - \omega) \right] \\ &\quad - R_0 + \frac{1}{2} \log \frac{\sigma_{X_0}^2}{D}. \end{aligned}$$

When $\epsilon_l = 0$ for $L - 1 \geq l \geq 1$ and $\tau_l = 1$ for $L \geq l \geq 2$, the recursion (15) becomes the following:

$$\left. \begin{aligned} \theta_L(\omega) &= \omega, \theta_{L-1}(\omega) = 2\omega \\ \theta_{l-1}(\omega) &= 2\theta_l(\omega) - \theta_{l+1}(\omega) \\ \text{for } L-1 \geq l \geq 2. \end{aligned} \right\} \quad (18)$$

Solving (18), we obtain $\theta_l(\omega) = (L-l+1)\omega$. The parametric form of $R_{\text{sum},L}(D, R_0)$ becomes

$$\left. \begin{aligned} \sigma_1^2 g_0(D, R_0) &= \theta_1(\omega) = L\omega, \\ R_{\text{sum},L}(D, R_0) &= \left(-\frac{L}{2} \right) \log(1 - \omega) \\ &\quad - R_0 + \frac{1}{2} \log \frac{\sigma_{X_0}^2}{D}. \end{aligned} \right\} \quad (19)$$

From (19), we have

$$\begin{aligned} R_{\text{sum},L}(D, R_0) &= \left(-\frac{L}{2} \right) \log \left(1 - \frac{\sigma_1^2}{L} g_0(D, R_0) \right) \\ &\quad - R_0 + \frac{1}{2} \log \frac{\sigma_{X_0}^2}{D}. \end{aligned} \quad (20)$$

In particular, by letting $R_0 = 0$ and $L \rightarrow \infty$ in (20), we have

$$\begin{aligned} \lim_{L \rightarrow \infty} R_{\text{sum},L}(D, 0) &= \frac{1}{2} \sigma_1^2 g_0(D, 0) + \frac{1}{2} \log \frac{\sigma_{X_0}^2}{D} \\ &= \frac{\sigma_1^2}{2\sigma_{X_0}^2} \left[\frac{\sigma_{X_0}^2}{D} - 1 \right] + \frac{1}{2} \log \frac{\sigma_{X_0}^2}{D}. \end{aligned}$$

The above formula coincides with the rate distortion function for the quadratic Gaussian CEO problem obtained by Oohama [7]. Hence, our solution to $R_{\text{sum},L}(D, R_0)$ includes the previous result on the Gaussian CEO problem as a special case.

V. PROOFS OF THE RESULTS

In this section we prove Theorem 2 and Lemma 1 stated in Section III and prove Lemma 2 stated in Section IV.

A. Derivation of the Outer Bound

In this subsection we prove $\hat{\mathcal{R}}_L^{(\text{out})}(D) \subseteq \mathcal{R}_L^{(\text{out})}(D)$ stated in Theorem 2.

Proof of $\hat{\mathcal{R}}_L^{(\text{out})}(D) \subseteq \mathcal{R}_L^{(\text{out})}(D)$: Set

$$\begin{aligned} \hat{J}_S(D, r_0, r^{L-2}, r_S | r_{S^c}, R_0) \\ \triangleq \left[\frac{1}{2} \log^+ \left[\frac{G(D, r_0, r^{L-2}) \sigma_{X_0}^2}{F(r_{S^c}) \{1 + \sigma_{X_0}^2 f_0(r_{S^c})\} D} \right] + \sum_{i=1}^L r_i - R_0 \right]^+. \end{aligned}$$

We first observe that

$$\begin{aligned} \hat{J}_S(D, r_0, r^{L-2}, r_S | r_{S^c}, r_0) \\ = \frac{1}{2} \left[\log^+ \left[\frac{G(D, r_0, r^{L-2}) \sigma_{X_0}^2}{F(r_{S^c}) \{1 + \sigma_{X_0}^2 f_0(r_{S^c})\} D} \right] + \sum_{i=1}^L 2r_i - 2r_0 \right]^+ \\ \geq \frac{1}{2} \left[\log \left[\frac{G(D, r_0, r^{L-2}) \sigma_{X_0}^2}{F(r_{S^c}) \{1 + \sigma_{X_0}^2 f_0(r_{S^c})\} D} \right] + \sum_{i=1}^L 2r_i - 2r_0 \right]^+ \\ = J_S(D, r_0, r^{L-2}, r_S | r_{S^c}). \end{aligned} \quad (21)$$

Then, we have the following.

$$\begin{aligned} \hat{\mathcal{R}}_L^{(\text{out})}(D) \\ \stackrel{(a)}{\subseteq} \left\{ (R_0, R^L) : \text{There exists a nonnegative vector } (r_0, r^L) \text{ such that} \right. \\ \left. R_0 \geq r_0 \geq \frac{1}{2} \log^+ \left[\frac{\sigma_{X_0}^2}{\{1 + \sigma_{X_0}^2 f_0(r^L)\} D} \right], \right. \\ \left. \sum_{i \in S} R_i \geq \hat{J}_S(D, r_0, r^{L-2}, r_S | r_{S^c}, R_0) \right. \\ \left. \text{for any } S \subseteq \Lambda. \right\} \\ \stackrel{(b)}{=} \left\{ (R_0, R^L) : \text{There exists a nonnegative vector } r^L \text{ such that} \right. \\ \left. R_0 \geq \frac{1}{2} \log^+ \left[\frac{\sigma_{X_0}^2}{\{1 + \sigma_{X_0}^2 f_0(r^L)\} D} \right], \right. \\ \left. \sum_{i \in S} R_i \geq \hat{J}_S(D, R_0, r^{L-2}, r_S | r_{S^c}, R_0) \right. \\ \left. \text{for any } S \subseteq \Lambda. \right\} \end{aligned}$$

$$\subseteq \left\{ (R_0, R^L) : \text{There exists a nonnegative vector } (r_0, r^L) \text{ such that} \right. \\ R_0 \geq r_0 \geq \frac{1}{2} \log \left[\frac{\sigma_{X_0}^2}{\{1 + \sigma_{X_0}^2 f_0(r^L)\} D} \right], \\ \sum_{i \in S} R_i \geq \hat{J}_S(D, r_0, r^{L-2}, r_S | r_{S^c}, r_0) \\ \left. \text{for any } S \subseteq \Lambda. \right\}.$$

$$\stackrel{(c)}{\subseteq} \left\{ (R_0, R^L) : \text{There exists a nonnegative vector } (r_0, r^L) \text{ such that} \right. \\ R_0 \geq r_0 \geq \frac{1}{2} \log \left[\frac{\sigma_{X_0}^2}{\{1 + \sigma_{X_0}^2 f_0(r^L)\} D} \right], \\ \sum_{i \in S} R_i \geq J_S(D, r_0, r^{L-2}, r_S | r_{S^c}) \\ \left. \text{for any } S \subseteq \Lambda. \right\} = \mathcal{R}_L^{(\text{out})}(D).$$

Step (a) follows from the definition of $\hat{J}_S(D, R_0, r^{L-2}, r_S | r_{S^c}, R_0)$ and the nonnegative property of R^L . Step (b) follows from that $\hat{J}_S(D, r_0, r^{L-2}, r_S | r_{S^c}, R_0)$ is a monotone decreasing function of r_0 . Step (c) follows from (21). Thus $\hat{\mathcal{R}}_L^{(\text{out})}(D) \subseteq \mathcal{R}_L^{(\text{out})}(D)$ is proved. ■

B. Derivation of the Inner Bound

In this subsection we prove $\mathcal{R}_L^{(\text{in})}(D) \subseteq \tilde{\mathcal{R}}_L^{(\text{in})}(D)$ stated in Theorem 2. We first derive a preliminary result on a form of $\mathcal{R}_L^{(\text{in})}(D)$. Fix $R_0 \geq r_0$ and set

$$\mathcal{R}_L^{(\text{in})}(r_0^L | R_0) \triangleq \{(R_1, \dots, R_L) : (R_0, R_1, \dots, R_L) \in \mathcal{R}_L^{(\text{in})}(r_0^L)\}.$$

Let $(\Lambda, \tilde{\rho})$, $\tilde{\rho} = \{\tilde{\rho}_S(r_S | r_{S^c})\}_{S \subseteq \Lambda}$ be a co-polymatroid defined in Property 4. Expression of $\mathcal{R}_L^{(\text{in})}(r_0^L | R_0)$ using $(\Lambda, \tilde{\rho})$ is

$$\mathcal{R}_L^{(\text{in})}(r_0^L | R_0) = \{(R_1, \dots, R_L) : \sum_{i \in S} R_i \geq \tilde{\rho}_S(r_S | r_{S^c}) \\ \text{for any } S \subseteq \Lambda.\}.$$

The set $\mathcal{R}_L^{(\text{in})}(r_0^L | R_0)$ forms a kind of polytope, which is called a *co-polymatroidal polytope* in the terminology of matroid theory. It is well known as a property of this kind of polytope that the polytope $\mathcal{R}_L^{(\text{in})}(r_0^L | R_0)$ consists of $L!$ end-points whose components are given by

$$\left. \begin{aligned} & R_{\pi(i)} \\ &= \tilde{\rho}_{\{\pi(i), \dots, \pi(L)\}}(r_{\{\pi(i), \dots, \pi(L)\}} | r_{\{\pi(1), \dots, \pi(i-1)\}}) \\ &\quad - \tilde{\rho}_{\{\pi(i+1), \dots, \pi(L)\}}(r_{\{\pi(i+1), \dots, \pi(L)\}} | r_{\{\pi(1), \dots, \pi(i)\}}) \\ &\quad \text{for } i = 1, 2, \dots, L-1, \\ & R_{\pi(L)} = \tilde{\rho}_{\{\pi(L)\}}(r_{\pi(L)} | r_{\{\pi(1), \dots, \pi(L-1)\}}), \end{aligned} \right\} \quad (22)$$

where

$$\pi = \begin{pmatrix} 1 & \dots & i & \dots & L \\ \pi(1) & \dots & \pi(i) & \dots & \pi(L) \end{pmatrix} \in \Pi$$

is an arbitrary permutation on Λ . For each $\pi \in \Pi$ and $r_0^L \in \mathcal{B}_L(D)$, let $\mathcal{R}_{\pi, L}^{(\text{in})}(r_0^L)$ be the set of nonnegative vectors

$(R_0, R_1, \dots, R_L)$ satisfying

$$\left. \begin{aligned} & R_0 \geq r_0 \\ & R_{\pi(i)} \\ & \geq \tilde{\rho}_{\{\pi(i), \dots, \pi(L)\}}(r_{\{\pi(i), \dots, \pi(L)\}} | r_{\{\pi(1), \dots, \pi(i-1)\}}) \\ & \quad - \tilde{\rho}_{\{\pi(i+1), \dots, \pi(L)\}}(r_{\{\pi(i+1), \dots, \pi(L)\}} | r_{\{\pi(1), \dots, \pi(i)\}}) \\ & \quad \text{for } i = 1, 2, \dots, L-1, \\ & R_{\pi(L)} \geq \tilde{\rho}_{\{\pi(L)\}}(r_{\pi(L)} | r_{\{\pi(1), \dots, \pi(L-1)\}}). \end{aligned} \right\} \quad (23)$$

Then, we have

$$\mathcal{R}^{(\text{in})}(r_0^L) = \text{conv} \left\{ \bigcup_{\pi \in \Pi} \mathcal{R}_{\pi, L}^{(\text{in})}(r_0^L) \right\}.$$

Proof of $\mathcal{R}_L^{(\text{in})}(D) \subseteq \tilde{\mathcal{R}}_L^{(\text{in})}(D)$: Fix $\pi \in \Pi$ and $r_0^L \in \mathcal{B}_L(D)$ arbitrary. By (23), it suffices to show that for $r_0^L \in \mathcal{B}_L(D)$, $\mathcal{R}_{\pi, L}^{(\text{in})}(r_0^L) \subseteq \tilde{\mathcal{R}}_{\pi, L}^{(\text{in})}(D)$ to prove $\mathcal{R}_L^{(\text{in})}(D) \subseteq \tilde{\mathcal{R}}_L^{(\text{in})}(D)$. Let $V_i, i \in \{0\} \cup \Lambda$ be independent Gaussian random variables with mean 0 and variance $\sigma_{V_i}^2$. Suppose that V_0^L is independent of X_0^L . Define the Gaussian random variables $U_i, i \in \{0\} \cup \Lambda$ by

$$U_i \triangleq X_i + V_i, \quad i \in \{0\} \cup \Lambda.$$

From the above definition it is obvious that

$$\left. \begin{aligned} & U^L \rightarrow X^L \rightarrow X_0 \rightarrow U_0, \\ & U_S \rightarrow X_{S \cup \{0\}} \rightarrow X_{S^c} \rightarrow U_{S^c}, \end{aligned} \right\} \quad \text{for any } S \subseteq \Lambda. \quad (24)$$

For given $r_i \geq 0, i \in S$ and $D > 0$, set $\frac{1}{\sigma_{V_i}^2} = \frac{e^{2r_i} - 1}{\sigma_{N_i}^2}$, when $r_i > 0$. When $r_i = 0$, we choose U_i so that U_i takes the constant value zero. Define the sequence of random variables $\{\Omega_l\}_{l=0}^L$ by

$$\left. \begin{aligned} & \Omega_{L-1} = \frac{1 - e^{-2r_{L-1}}}{\sigma_{N_{L-1}}^2} \cdot U_{L-1} + \frac{1 - e^{-2r_L}}{\sigma_{N_L}^2} \cdot U_L \\ & \Omega_l = \frac{1}{1 + \sigma_{Z_{l+1}}^2 f_{l+1}(r_{l+1}^L)} \cdot \Omega_{l+1} + \frac{1 - e^{-2r_l}}{\sigma_{N_l}^2} \cdot U_l \\ & \quad \text{for } L-2 \geq l \geq 1 \\ & \Omega_0 = \frac{1}{1 + \sigma_{Z_1}^2 f_1(r^L)} \cdot \Omega_1. \end{aligned} \right\} \quad (25)$$

Note that $\Omega_0 = \Omega_0(U^L)$ is a linear function of U^L . Then, by an elementary computation, we have

$$\begin{aligned} X_0 &= \frac{1}{\frac{1}{\sigma_{X_0}^2} + \frac{1}{\sigma_{V_0}^2} + f_0(r^L)} \left[\frac{1}{\sigma_{V_0}^2} \cdot U_0 + \Omega_0(U^L) \right] \\ &\quad + \tilde{N}_0, \end{aligned} \quad (26)$$

where $\tilde{N}_0$ is a zero mean Gaussian random variable with variance

$$\left[\frac{1}{\sigma_{X_0}^2} + \frac{1}{\sigma_{V_0}^2} + f_0(r^L) \right]^{-1}.$$

$\tilde{N}_0$ is independent of (U_0, U^L) . Since $r_0^L \in \mathcal{B}_L(D)$, we have

$$\frac{e^{-2r_0}}{D} - \frac{1}{\sigma_{X_0}^2} \leq f_0(r^L). \quad (27)$$

We put

$$\frac{1}{\sigma_{V_0}^2} = \frac{1 - e^{-2r_0}}{D}. \quad (28)$$

Then, from (27) and (28), we have

$$\begin{aligned} & \left[\frac{1}{\sigma_{X_0}^2} + \frac{1}{\sigma_{V_0}^2} + f_0(r^L) \right]^{-1} \\ &= \left[\frac{1}{\sigma_{X_0}^2} + \frac{1-e^{-2r_0}}{D} + f_0(r^L) \right]^{-1} \leq D. \end{aligned} \quad (29)$$

Based on (26), (28), and (29), define the linear function $\tilde{\psi}$ of (U_0, U^L) by

$$\begin{aligned} \tilde{\psi}(U_0, U^L) &\triangleq \left[\frac{1}{\sigma_{X_0}^2} + \frac{1-e^{-2r_0}}{D} + f_0(r^L) \right]^{-1} \\ &\quad \times \left[\frac{1-e^{-2r_0}}{D} \cdot U_0 + \Omega_0(U^L) \right]. \end{aligned}$$

Then, we obtain

$$\begin{aligned} \mathbb{E} \left[X_0 - \tilde{\psi}(U_0, U^L) \right]^2 &= \mathbf{Var} \left[\tilde{N}_0 \right] \\ &= \left[\frac{1}{\sigma_{X_0}^2} + \frac{1-e^{-2r_0}}{D} + f_0(r^L) \right]^{-1} \leq D. \end{aligned} \quad (30)$$

From (24) and (30), we have $(U_0, U^L) \in \mathcal{G}(D)$. By simple computations, we can show that

$$\left. \begin{aligned} r_0 &= I(X_0; U_0 | U^L), \\ r_i &= I(X_i; U_i | X_0 Y^{L-1}), \\ &\quad \text{for any } i \in \Lambda, \\ &\quad \frac{1}{2} \log [F_S(r_S) \cdot \{1 + \sigma_{X_0}^2 f_0(r_S)\}] \\ &= I(X_0 Y^{L-1}; U_S), \\ &\quad \text{for any } S \subseteq \Lambda. \end{aligned} \right\} \quad (31)$$

Using (24) and (31), the $L+1$ inequalities of (23) are rewritten as

$$\begin{aligned} R_0 &\geq I(X_0; U_0 | U^L), \\ R_{\pi(i)} &\geq I(X_0 Y^{L-1}; U_{\pi(S_i)} | U_{\pi(S_i^c)}) \\ &\quad + I(X_{\pi(i)}; U_{\pi(i)} | X_0 Y^{L-1}) \\ &\quad - I(X_0 Y^{L-1}; U_{\pi(S_{i+1})} | U_{\pi(S_{i+1}^c)}) \\ &= I(X_0 Y^{L-1}; U_{\pi(i)} | U_{\pi(S_i^c)}) \\ &\quad + I(X_{\pi(i)}; U_{\pi(i)} | X_0 Y^{L-1} U_{\pi(S_i^c)}) \\ &= I(X_0 Y^{L-1} X_{\pi(i)}; U_{\pi(i)} | U_{\pi(S_i^c)}) \\ &= I(X_{\pi(i)}; U_{\pi(i)} | U_{\pi(S_i^c)}) \\ &\quad \text{for } i = 1, 2, \dots, L. \end{aligned}$$

Thus, we conclude that $(R_0, R_{\pi(1)}, \dots, R_{\pi(L)}) \in \tilde{\mathcal{R}}_{\pi, L}^{(\text{in})}(D)$.

C. Proofs of Lemmas 1 and 2

In this subsection we prove Lemmas 1 and 2. We first present a preliminary observation on $\mathcal{R}_L^{(\text{out})}(D)$. Fix $R_0 \geq r_0$ arbitrary and set

$$\begin{aligned} \mathcal{R}_L^{(\text{out})}(D, r_0^L | R_0) &\triangleq \{(R_1, \dots, R_L) : \\ &\quad (R_0, R_1, \dots, R_L) \in \mathcal{R}_L^{(\text{out})}(D, r_0^L)\}. \end{aligned}$$

Let (Λ, ρ) , $\rho = \{\rho_S(r_S | r_{S^c})\}_{S \subseteq \Lambda}$ be a co-polymatroid defined in Property 4. Expression of $\mathcal{R}_L^{(\text{out})}(D_0, r_0^L | R_0)$ using (Λ, ρ)

is

$$\mathcal{R}_L^{(\text{out})}(D, r_0^L | R_0) = \{(R_1, \dots, R_L) : \sum_{i \in S} R_i \geq \rho_S(r_S | r_{S^c}) \text{ for any } S \subseteq \Lambda\}.$$

The set $\mathcal{R}_L^{(\text{out})}(D, r_0^L | R_0)$ forms a co-polymatroidal polytope. The polytope $\mathcal{R}_L^{(\text{out})}(D, r_0^L | R_0)$ consists of $L!$ end-points whose components are given by

$$\left. \begin{aligned} & R_{\pi(i)} \\ &= \rho_{\{\pi(i), \dots, \pi(L)\}}(r_{\{\pi(i), \dots, \pi(L)\}} | r_{\{\pi(1), \dots, \pi(i-1)\}}) \\ &\quad - \rho_{\{\pi(i+1), \dots, \pi(L)\}}(r_{\{\pi(i+1), \dots, \pi(L)\}} | r_{\{\pi(1), \dots, \pi(i)\}}) \\ &\quad \text{for } i = 1, 2, \dots, L-1, \\ & R_{\pi(L)} = \rho_{\{\pi(L)\}}(r_{\pi(L)} | r_{\{\pi(1), \dots, \pi(L-1)\}}), \end{aligned} \right\} \quad (32)$$

where

$$\pi = \begin{pmatrix} 1 & \dots & i & \dots & L \\ \pi(1) & \dots & \pi(i) & \dots & \pi(L) \end{pmatrix} \in \Pi.$$

For each $\pi \in \Pi$ and $l = 1, 2, \dots, L$, set

$$\begin{aligned} \mathcal{B}_{\pi, l}(D) &\triangleq \{r_0^L : r_0^L \in \mathcal{B}_L(D) \text{ and} \\ &\quad r_{\pi(i)} = 0 \text{ for } i = l+1, \dots, L\}, \\ \partial \mathcal{B}_{\pi, l}(D) &\triangleq \{r_0^L : r_0^L \in \partial \mathcal{B}_L(D) \text{ and} \\ &\quad r_{\pi(i)} = 0 \text{ for } i = l+1, \dots, L\}. \end{aligned}$$

In particular, when π is the identity map, we omit π to write $\mathcal{B}_l(D)$ and $\partial \mathcal{B}_l(D)$. By Property 3, when $r_0^L \in \mathcal{B}_{\pi, l}(D)$, the end-point given by (32) becomes

$$\left. \begin{aligned} & R_{\pi(i)} \\ &= \rho_{\{\pi(i), \dots, \pi(l)\}}(r_{\{\pi(i), \dots, \pi(l)\}} | r_{\{\pi(1), \dots, \pi(i-1)\}}) \\ &\quad - \rho_{\{\pi(i+1), \dots, \pi(l)\}}(r_{\{\pi(i+1), \dots, \pi(l)\}} | r_{\{\pi(1), \dots, \pi(i)\}}) \\ &\quad \text{for } i = 1, 2, \dots, l-1, \\ & R_{\pi(l)} = \rho_{\{\pi(l)\}}(r_{\pi(l)} | r_{\{\pi(1), \dots, \pi(l-1)\}}), \\ & R_{\pi(i)} = 0, \text{ for } i = l+1, \dots, L. \end{aligned} \right\} \quad (33)$$

Next, we present a lemma on a property of $G(D, r_0, r^{L-1})$.

Lemma 5: For $r_0^L \in \mathcal{B}_l(D)$, $G(D, r_0, r^{L-2})$ is computed as

$$G(D, r_0, r^{L-2})|_{r_{l+1}^L = \mathbf{0}} = \prod_{k=1}^l [1 + \sigma_{Z_k}^2 g_k(D, r_0, r^{k-1})].$$

Proof: By Property 1 part c), for $l+1 \leq k \leq L$

$$0 \leq g_k(D, r_0, r^{k-1}) \leq f(r_k^L) = 0.$$

Hence, the result of Lemma 5 follows. $\blacksquare$

Proof of Lemma 1: Fix $\pi \in \Pi$ and $r_0^L \in \mathcal{B}_L(D)$ arbitrary. Let (R_0, R^L) be a nonnegative rate vector such that $R_0 \geq r_0$ and L components of R^L satisfy (32). To prove Lemma 1, it suffices to show that this nonnegative vector belongs to $\mathcal{R}_L^{(\text{in})}(D)$. For $l = 1, 2, \dots, L$, we prove the claim that under the MI condition, if $r_0^L \in \mathcal{B}_{\pi, l}(D)$, then, the rate vector (R_0, R^L) satisfying $R_0 \geq r_0$ and (33) belongs to $\mathcal{R}_L^{(\text{in})}(D)$. We prove this claim by induction with respect to l . When $l = 1$, from (33), we have

$$\left. \begin{aligned} & R_{\pi(1)} = \rho_{\{\pi(1)\}}(r_{\pi(1)}), \\ & R_{\pi(i)} = 0, \text{ for } i = 2, \dots, L. \end{aligned} \right\} \quad (34)$$

The function $\rho_{\{\pi(1)\}}(r_{\pi(1)})$ is computed as

$$\begin{aligned} & \rho_{\{\pi(1)\}}(r_{\pi(1)}) \\ &= J_{\{\pi(1)\}}(D, r_0, r^{L-2}, r_{\pi(1)} | r_{\{\pi(1)\}^c} |_{r_{\{\pi(1)\}^c} = \mathbf{0}}) \\ &= \frac{1}{2} \log^+ \left[\frac{G(D, r_0, r^{L-2}) |_{r_{\{\pi(1)\}^c} = \mathbf{0}} \sigma_{X_0}^2 e^{-2r_0} e^{2r_{\pi(1)}}}{D} \right]. \end{aligned} \quad (35)$$

By the above form of $\rho_{\{\pi(1)\}}(r_{\pi(1)})$ and

$$\frac{\sigma_{X_0}^2 e^{-2r_0}}{D} \geq \frac{\sigma_{X_0}^2 e^{-2R_0}}{D} > 1,$$

$\rho_{\{\pi(1)\}}(r_{\pi(1)})$ is positive. Since $r_0^L \in \mathcal{B}_{\pi, l}(D)$, we can decrease $r_{\pi(1)}$ keeping $r_0^L \in \mathcal{B}_{\pi, 1}(D)$ so that it arrives at $r_{\pi(1)}^* = 0$ or a positive $r_{\pi(1)}^*$ satisfying

$$\begin{aligned} & (r_0, r_{\pi(1)}^*, r_{\{\pi(1)\}^c}) \\ &= (r_0, r_{\pi(1)}^*, \underbrace{0, \dots, 0}_{L-1}) \in \partial \mathcal{B}_{\pi, 1}(D). \end{aligned} \quad (36)$$

Let $(R_0, R_{\pi(1)}^*, \dots, R_{\pi(L)}^*)$ be a rate vector corresponding to $(r_0, r_{\pi(1)}^*, r_{\{\pi(1)\}^c})$. If $r_{\pi(1)}^* = 0$, then by Property 3 part b), $\rho_{\{\pi(1)\}}(r_{\pi(1)})$ must be zero. This contradicts the fact that $\rho_{\{\pi(1)\}}(r_{\pi(1)})$ is positive. Therefore, $r_{\pi(1)}^*$ must be positive. Then, from (36), we have

$$\begin{aligned} & (R_0, R_{\pi(1)}^*, \dots, R_{\pi(L)}^*) \\ &= (R_0, R_{\pi(1)}^*, \underbrace{0, \dots, 0}_{L-1}) \in \mathcal{R}_L^{(\text{in})}(D). \end{aligned}$$

On the other hand, by Lemma 5, we have

$$\begin{aligned} & G(D, r_0, r^{L-2}) |_{r_{\{\pi(1)\}^c} = \mathbf{0}} \\ &= G(D, r_0, r^{L-2}) |_{r_{\pi(1)+1}^L = \mathbf{0}, r^{\pi(1)-1} = \mathbf{0}} \\ &= \prod_{k=1}^{\pi(1)} [1 + \sigma_{Z_k}^2 g_k(D, r_0, r^{k-1})] \Big|_{r^{\pi(1)-1} = \mathbf{0}}. \end{aligned} \quad (37)$$

From (35) and (37), we can see that $G(D, r_0, r^{L-2}) |_{r_{\{\pi(1)\}^c} = \mathbf{0}}$ does not depend on $r_{\pi(1)}$. This implies that $\rho_{\{\pi(1)\}}(r_{\pi(1)})$ is a monotone increasing function of $r_{\pi(1)}$. Then, we have $R_{\pi(1)} \geq R_{\pi(1)}^*$. Hence, we have

$$\begin{aligned} & (R_0, R_{\pi(1)}, \dots, R_{\pi(L)}) \\ &= (R_0, R_{\pi(1)}, \underbrace{0, \dots, 0}_{L-1}) \in \mathcal{R}_L^{(\text{in})}(D). \end{aligned}$$

Thus, the claim holds for $l = 1$. We assume that the claim holds for $l - 1$. Since $f_0(r_0^L)$ is a monotone increasing function of $r_{\pi(l)}$ on $\mathcal{B}_{\pi, l}(D)$, we can decrease $r_{\pi(l)}$ keeping $r_0^L \in \mathcal{B}_{\pi, l}(D)$ so that it arrives at $r_{\pi(l)}^* = 0$ or a positive $r_{\pi(l)}^*$ satisfying

$$(r_0, r_{\pi(l)}^*, r_{\{\pi(l)\}^c}) \in \partial \mathcal{B}_{\pi, l}(D). \quad (38)$$

Let $(R_0, R_{\pi(1)}^*, \dots, R_{\pi(L)}^*)$ be a rate vector corresponding to $(r_0, r_{\pi(l)}^*, r_{\{\pi(l)\}^c})$. By Property 4 part b) and the MI condition, the l functions

$$\begin{aligned} & \rho_{\{\pi(i), \dots, \pi(l)\}}(r_{\{\pi(i), \dots, \pi(l)\}} | r_{\{\pi(1), \dots, \pi(i-1)\}}) \\ & - \rho_{\{\pi(i+1), \dots, \pi(l)\}}(r_{\{\pi(i+1), \dots, \pi(l)\}} | r_{\{\pi(1), \dots, \pi(i)\}}) \\ & \text{for } i = 1, 2, \dots, l-1, \\ & \rho_{\{\pi(l)\}}(r_{\pi(l)} | r_{\{\pi(1), \dots, \pi(l-1)\}}), \end{aligned}$$

appearing in the right members of (33) are monotone increasing functions of $r_{\pi(l)}$. Then, from (33), we have

$$\left. \begin{aligned} R_{\pi(i)} &\geq R_{\pi(i)}^* \text{ for } i = 1, 2, \dots, l, \\ R_{\pi(i)} &= R_{\pi(i)}^* = 0 \text{ for } i = l+1, \dots, L. \end{aligned} \right\} \quad (39)$$

When $r_{\pi(l)}^* = 0$, we have $(r_0, r_{\pi(l)}^*, r_{\{\pi(l)\}^c}) \in \mathcal{B}_{\pi, l-1}(D)$. Then, by induction hypothesis, we have

$$(R_0, R_{\pi(1)}^*, \dots, R_{\pi(L)}^*) \in \mathcal{R}_L^{(\text{in})}(D).$$

When $r_{\pi(l)}^* > 0$, from (38), we have

$$(R_0, R_{\pi(1)}^*, \dots, R_{\pi(L)}^*) \in \mathcal{R}_L^{(\text{in})}(D).$$

Hence, by (39), we have

$$\begin{aligned} & (R_0, R_{\pi(1)}, \dots, R_{\pi(L)}) \\ &= (R_0, R_{\pi(1)}, \dots, R_{\pi(l)}, \underbrace{0, \dots, 0}_{L-l}) \in \mathcal{R}_L^{(\text{in})}(D). \end{aligned}$$

Thus, the claim holds for l . This completes the proof of Lemma 1. $\blacksquare$

Proof of Lemma 2: For $R_0 > 0$ and for $1 \leq l \leq L$, set

$$\begin{aligned} \mathcal{B}_l(D|R_0) &\triangleq \{r^l : (R_0, r^L) \in \mathcal{B}_l(D)\}, \\ \partial \mathcal{B}_l(D|R_0) &\triangleq \{r^l : (R_0, r^L) \in \partial \mathcal{B}_l(D)\}. \end{aligned}$$

We first observe that

$$\begin{aligned} & R_{\text{sum}, L}^{(1)}(D, R_0) \\ &= \min_{1 \leq l \leq L} \left[\min_{r^l \in \mathcal{B}_l(D|R_0)} J_\Lambda(D, R_0, r^{L-2}, r^L) |_{r_{l+1}^L = \mathbf{0}} \right], \\ & R_{\text{sum}, L}^{(u)}(D, R_0) \\ &= \min_{1 \leq l \leq L} \left[\min_{r^l \in \partial \mathcal{B}_l(D|R_0)} K_\Lambda(r^l) \right]. \end{aligned}$$

We compute $J_\Lambda(D, R_0, r^{L-2}, r^L) |_{r_{l+1}^L = \mathbf{0}}$. By Lemma 5, for $r^l \in \mathcal{B}_l(D|R_0)$

$$G(D, R_0, r^{L-2}) |_{r_{l+1}^L = \mathbf{0}} = \prod_{k=1}^l [1 + \sigma_{Z_k}^2 g_k(D, R_0, r^{k-1})].$$

From the above formula, we can see that for $r^l \in \mathcal{B}_l(D|R_0)$, $G(D, R_0, r^{L-2}) |_{r_{l+1}^L = \mathbf{0}}$ is a function of r^{l-1} . We denote this function by $G(D, R_0, r^{l-1})$, that is,

$$G(D, R_0, r^{l-1}) \triangleq \prod_{k=1}^l [1 + \sigma_{Z_k}^2 g_k(D, R_0, r^{k-1})].$$

Then, for $r^l \in \mathcal{B}_l(D|R_0)$,

$$\begin{aligned} & J_\Lambda(D, R_0, r^{L-2}, r^L) |_{r_{l+1}^L = \mathbf{0}} \\ &= \frac{1}{2} \log^+ \left[G(D, R_0, r^{l-1}) \cdot \frac{\sigma_{X_0}^2}{D} e^{-2R_0} \prod_{i=1}^l e^{2r_i} \right]. \end{aligned} \quad (40)$$

We denote the right member of (40) by $J_\Lambda(D, R_0, r^{l-1}, r^l)$. Using this function, $R_{\text{sum}, L}^{(1)}(D, R_0)$ can be written as

$$R_{\text{sum}, L}^{(1)}(D, R_0) = \min_{1 \leq l \leq L} \left[\min_{r^l \in \mathcal{B}_l(D|R_0)} J_\Lambda(D, R_0, r^{l-1}, r^l) \right].$$

Note here that $J_\Lambda(D, R_0, r^{l-1}, r^l)$ is a monotone increasing function of r_l . To prove $R_{\text{sum}, L}^{(l)}(D, R_0) \geq R_{\text{sum}, L}^{(u)}(D, R_0)$, it suffices to show that for $1 \leq l \leq L$,

$$\min_{r^l \in \mathcal{B}_l(D|R_0)} J_\Lambda(D, R_0, r^{l-1}, r^l) \geq \min_{r^l \in \partial \mathcal{B}_l(D|R_0)} K_\Lambda(r^l).$$

We prove this claim by induction with respect to l . When $l = 1$, the function $J_\Lambda(D, R_0, r_1)$ is computed as

$$\begin{aligned} J_\Lambda(D, R_0, r_1) &= \frac{1}{2} \log^+ \left[\frac{\{1 + \sigma_{Z_1}^2 g_1(D, R_0)\} \sigma_{X_0}^2 e^{-2R_0} e^{2r_1}}{D} \right] \\ &= \frac{1}{2} \log^+ \left[\frac{\sigma_{X_0}^2 e^{-2R_0} e^{2r_1}}{\{1 - \sigma_{Z_1}^2 g_0(D, R_0)\} D} \right]. \end{aligned}$$

Since $\frac{\sigma_{X_0}^2 e^{-2R_0}}{D} > 1$, $J_\Lambda(D, R_0, r_1)$ is positive. Since $J_\Lambda(D, R_0, r_1)$ is a monotone increasing function of r_1 , the minimum of this function is attained by $r_1^* = 0$ or a positive r_1^* satisfying $r_1^* \in \partial \mathcal{B}_1(D|R_0)$. If $r_1^* = 0$, then, by Property 3 part b), $J_\Lambda(D, R_0, r_1)$ must be zero. This contradicts that $J_\Lambda(D, R_0, r_1)$ is positive. Therefore, r_1^* must be positive. Then, by $r_1^* \in \partial \mathcal{B}_1(D|R_0)$, we have

$$\begin{aligned} J_\Lambda(D, R_0, r_1) &\geq J_\Lambda(D, R_0, r_1^*) \\ &= K_\Lambda(r_1^*) \geq \min_{r_1 \in \partial \mathcal{B}_1(D|R_0)} K_\Lambda(r_1). \end{aligned}$$

Thus, the claim holds for $l = 1$. We assume that the claim holds for $l - 1$. Since $J_\Lambda(D, R_0, r^{l-1}, r^l)$ is a monotone increasing function of r_l , the minimum of this function is attained by $r_l^* = 0$ or a positive r_l^* satisfying $(r^{l-1}, r_l^*) \in \partial \mathcal{B}_l(D|R_0)$. When $r_l^* = 0$, we have $r^{l-1} \in \mathcal{B}_{l-1}(D|R_0)$ and

$$J_\Lambda(D, R_0, r^{l-1}, r^l) \geq J_\Lambda(D, R_0, r^{l-1}, r^{l-1} r_l^*). \quad (41)$$

Computing $J_\Lambda(D, R_0, r^{l-1}, r^{l-1} r_l^*)$, we obtain

$$\begin{aligned} &J_\Lambda(D, R_0, r^{l-1}, r^{l-1} r_l^*) \\ &= J_\Lambda(D, R_0, r^{L-2}, r^L) \Big|_{r_l^L = 0} \\ &= \frac{1}{2} \log^+ \left[G(D, R_0, r^{L-2}) \cdot \frac{\sigma_{X_0}^2}{D} e^{-2R_0} \prod_{i=1}^{L-1} e^{2r_i} \right] \\ &= J_\Lambda(D, R_0, r^{L-2}, r^{L-1}). \end{aligned} \quad (42)$$

Combining (41) and (42), we have

$$J_\Lambda(D, R_0, r^{l-1}, r^l) \geq J_\Lambda(D, R_0, r^{L-2}, r^{L-1}). \quad (43)$$

On the other hand, by induction hypothesis, we have

$$J_\Lambda(D, R_0, r^{L-2}, r^{L-1}) \geq \min_{r^{L-1} \in \partial \mathcal{B}_{L-1}(D|R_0)} K_\Lambda(r^{L-1}). \quad (44)$$

Combining (43) and (44), we have

$$\begin{aligned} J_\Lambda(D, R_0, r^{l-1}, r^l) &\geq \min_{r^{L-1} \in \partial \mathcal{B}_{L-1}(D|R_0)} K_\Lambda(r^{L-1}) \\ &\geq \min_{r^l \in \partial \mathcal{B}_l(D|R_0)} K_\Lambda(r^l). \end{aligned}$$

When $r_l^* > 0$, we have

$$\begin{aligned} J_\Lambda(D, R_0, r_{l-1}, r^l) &\geq J_\Lambda(D, R_0, r_{l-1}, r_{l-1}^* r_l^*) \\ &= K_\Lambda(r_{l-1}^* r_l^*) \\ &\geq \min_{r^l \in \partial \mathcal{B}_l(D|R_0)} K_\Lambda(r^l), \end{aligned}$$

where the second equality follows from $(r^{l-1}, r_l^*) \in \partial \mathcal{B}_l(D|R_0)$. Thus, the claim holds for l , completing the proof. ■

VI. CONCLUSIONS

We have considered the Gaussian many-help-one problem and given a partial solution to this problem by deriving explicit outer bound of the rate distortion region for the case where information sources satisfy the TS condition. Furthermore, we established a sufficient condition under which this outer bound is tight. We have determined the sum rate part of the rate distortion region for the case where information sources satisfy the TS condition.

For the case that information sources do not satisfy the TS condition we can not derive an outer bound having a similar form of $\mathcal{R}^{(\text{out})}(D)$ since the proof of the converse coding theorem depends heavily on this property of information sources. Hence the complete solution is still lacking for Gaussian information sources with general correlation.

APPENDIX

A. Proof of Proposition 1

In this appendix we prove Proposition 1. To prove this proposition we give some preparations. For $0 \leq l \leq L - 2$, we set

$$\begin{aligned} \eta_l &= \eta_l(D, r_0, r^l) \\ &\triangleq \begin{cases} g_0(D, r_0), & \text{for } l = 0, \\ g_l(D, r_0, r^{l-1}) - \frac{1}{\sigma_{N_l}^2} (1 - e^{-2r_l}), & \text{for } 1 \leq l \leq L - 2. \end{cases} \end{aligned}$$

For $1 \leq l \leq L - 2$, and $a < \frac{1}{\sigma_{Z_l}^2}$, define

$$\tau_l(a) \triangleq \frac{[a]^+}{1 - \sigma_{Z_l}^2 [a]^+} - \frac{1}{\sigma_{N_l}^2} (1 - e^{-2r_l}).$$

Then, $\{\eta_l\}_{l=0}^{L-2}$ satisfies the following:

$$\begin{aligned} \eta_l(D, r_0, r^l) &= \tau_l(\eta_{l-1}(D, r_0, r^{l-1})) \\ &\quad \text{for } 1 \leq l \leq L - 2. \end{aligned} \quad (45)$$

Fix $a < \frac{1}{\sigma_{Z_{k+1}}^2}$ and set

$$\begin{aligned} p_k(a) &\triangleq \sup \left\{ p : \log \frac{1 - \sigma_{Z_{k+1}}^2 [a]^+}{1 - \sigma_{Z_{k+1}}^2 [b]^+} \geq p(b - a) \right. \\ &\quad \left. \text{for any } b < \frac{1}{\sigma_{Z_{k+1}}^2} \right\}. \end{aligned}$$

By a simple computation we have

$$\begin{aligned} p_k(a) &= \begin{cases} \frac{\sigma_{Z_{k+1}}^2}{1 - \sigma_{Z_{k+1}}^2 a}, & \text{for } 0 \leq a < \frac{1}{\sigma_{Z_{k+1}}^2}, \\ 0, & \text{for } a < 0 \end{cases} \\ &\leq \frac{\sigma_{Z_{k+1}}^2}{1 - \sigma_{Z_{k+1}}^2 a} \text{ for } a < \frac{1}{\sigma_{Z_{k+1}}^2}. \end{aligned} \quad (46)$$

Fix $a < \frac{1}{\sigma_{Z_j}^2}$ and set

$$\begin{aligned} q_j(a) &\triangleq \sup \left\{ q : \tau_j(b) - \tau_j(a) \geq q(b - a) \right. \\ &\quad \left. \text{for any } b < \frac{1}{\sigma_{Z_j}^2} \right\}. \end{aligned}$$

By a simple computation we have

$$q_j(a) = \begin{cases} \frac{1}{(1-\sigma_{Z_j}^2 a)^2}, & \text{for } 0 \leq a < \frac{1}{\sigma_{Z_j}^2}, \\ 0, & \text{for } a < 0 \\ \frac{1}{(1-\sigma_{Z_j}^2 a)^2}, & \text{for } a < \frac{1}{\sigma_{Z_j}^2}. \end{cases} \quad (47)$$

Proof of Proposition 1: Let $\mathcal{L}$ be a set of integers l such that $\eta_l(D, r_0, r^l)$ is positive for some $r_0^L \in \mathcal{B}_L(D)$. From (45), there exists a unique integer $1 \leq L^* \leq L-2$ such that $\mathcal{L} = \{0, 1, \dots, L^*\}$. Using $\{\eta_l\}_{l=1}^{L-2}$ and L^* , $\log G(D, r_0, r^{L-2})$ can be rewritten as

$$\begin{aligned} \log G(D, r_0, r^{L-2}) &= \sum_{k=1}^{L-1} \log \{1 + \sigma_{Z_k}^2 g_l(D, r_0, r^{k-1})\} \\ &= \sum_{k=1}^{L-1} \log \left[\frac{1}{1 - \sigma_{Z_k}^2 [\eta_{k-1}(D, r_0, r^{k-1})]^+} \right] \\ &= \sum_{k=0}^{L-2} \log \left[\frac{1}{1 - \sigma_{Z_{k+1}}^2 [\eta_k(D, r_0, r^k)]^+} \right] \\ &= \sum_{k=0}^{L^*} \log \left[\frac{1}{1 - \sigma_{Z_{k+1}}^2 [\eta_k(D, r_0, r^k)]^+} \right] \end{aligned} \quad (48)$$

Fix nonnegative vector r^L . For each $s_l \geq r_l$, $1 \leq l \leq L-2$, let $G(s_l)$ be a function obtained by replacing r_l in $G(D, r_0, r^{L-2})$ with s_l , that is

$$G(s_l) \triangleq G(D, r_0, r^{l-1}, s_l, r_{l+1}^{L-2}).$$

It is obvious that when $s_l = r_l$,

$$G(r_l) = G(D, r_0, r^{l-1}, r_l, r_{l+1}^{L-2}) = G(D, r_0, r^{L-2}).$$

By Property 2 part b), we have $G(s_l) \leq G(r_l)$ for $1 \leq l \leq L-2$. For each $s_k \geq r_k$, $l \leq k \leq L-2$, let $\eta_k(s_l)$ be a function obtained by replacing r_l in $\eta_k(D, r_0, r^k)$ with s_l , that is

$$\eta_k(s_l) \triangleq \eta_k(D, r_0, r^{l-1}, s_l, r_{l+1}^k).$$

It is obvious that when $s_l = r_l$,

$$\eta_k(r_l) = \eta_k(D, r_0, r^{l-1}, r_l, r_{l+1}^k) = \eta_k(D, r_0, r^k).$$

By Property 1 part b), we have $\eta_k(s_l) \leq \eta_k(r_l)$ for $l \leq k \leq L-2$. For each $l = 1, \dots, L^*$, we evaluate an upper bound of $\log G(s_l) - \log G(r_l)$. Using (48), we have

$$\begin{aligned} \log \frac{G(s_l)}{G(r_l)} &= \sum_{k=0}^{L^*} \log \left[\frac{1 - \sigma_{Z_{k+1}}^2 [\eta_k(r_l)]^+}{1 - \sigma_{Z_{k+1}}^2 [\eta_k(s_l)]^+} \right] \\ &= \sum_{k=l}^{L^*} \log \left[\frac{1 - \sigma_{Z_{k+1}}^2 [\eta_k(r_l)]^+}{1 - \sigma_{Z_{k+1}}^2 [\eta_k(s_l)]^+} \right]. \end{aligned} \quad (49)$$

By definition of $p_k(\cdot)$, we have

$$\begin{aligned} \log \left[\frac{1 - \sigma_{Z_{k+1}}^2 [\eta_k(r_l)]^+}{1 - \sigma_{Z_{k+1}}^2 [\eta_k(s_l)]^+} \right] &\geq p_k(\eta_k(r_l)) [\eta_k(s_l) - \eta_k(r_l)] \\ &\geq \frac{\sigma_{Z_{k+1}}^2}{1 - \sigma_{Z_{k+1}}^2 \eta_k(r_l)} [\eta_k(s_l) - \eta_k(r_l)], \end{aligned} \quad (50)$$

where the last inequality follows from $\eta_k(s_l) \leq \eta_k(r_l)$ and (46). From (49) and (50), we have

$$\log \frac{G(s_l)}{G(r_l)} \geq \sum_{k=l}^{L^*} \frac{\sigma_{Z_{k+1}}^2}{1 - \sigma_{Z_{k+1}}^2 \eta_k(r_l)} (\eta_k(s_l) - \eta_k(r_l)). \quad (51)$$

By definition of $q_j(\cdot)$ and (45), for $l+1 \leq j \leq k$, we have

$$\begin{aligned} \eta_j(s_l) - \eta_j(r_l) &\geq q_j(\eta_{j-1}(r_l)) [\eta_{j-1}(s_l) - \eta_{j-1}(r_l)] \\ &\geq \frac{1}{(1 - \sigma_{Z_j}^2 \eta_{j-1}(r_l))^2} [\eta_{j-1}(s_l) - \eta_{j-1}(r_l)], \end{aligned} \quad (52)$$

where the last inequality follows from $\eta_{j-1}(s_l) \leq \eta_{j-1}(r_l)$ and (47). Using (52) iteratively for $l+1 \leq j \leq k$, we obtain

$$\begin{aligned} \eta_k(s_l) - \eta_k(r_l) &\geq (\eta_l(s_l) - \eta_l(r_l)) \prod_{j=l+1}^k \frac{1}{(1 - \sigma_{Z_j}^2 \eta_{j-1})^2}. \end{aligned} \quad (53)$$

Observe that

$$\begin{aligned} \eta_l(s_l) - \eta_l(r_l) &= \frac{1}{\sigma_{N_l}^2} [e^{-2s_l} - e^{-2r_l}] \\ &\geq -\frac{2e^{-2r_l}}{\sigma_{N_l}^2} (s_l - r_l). \end{aligned} \quad (54)$$

From (53) and (54), we have

$$\begin{aligned} \eta_k(s_l) - \eta_k(r_l) &\geq -\frac{2e^{-2r_l}}{\sigma_{N_l}^2} (s_l - r_l) \prod_{j=l+1}^k \frac{1}{(1 - \sigma_{Z_j}^2 \eta_{j-1})^2} \\ &\geq -\frac{2}{\sigma_{N_l}^2} (s_l - r_l) \prod_{j=l+1}^k \frac{1}{(1 - \sigma_{Z_j}^2 \eta_{j-1})^2}. \end{aligned} \quad (55)$$

From (51) and (55), we have

$$\begin{aligned} \frac{1}{2} \log \frac{G(s_l)}{G(r_l)} &\geq -(s_l - r_l) \sum_{k=l}^{L^*} \frac{\sigma_{Z_{k+1}}^2}{\sigma_{N_l}^2} \frac{1}{1 - \sigma_{Z_{k+1}}^2 \eta_k} \prod_{j=l+1}^k \frac{1}{(1 - \sigma_{Z_j}^2 \eta_{j-1})^2}. \end{aligned} \quad (56)$$

By Property 1 part b) and the definition of η_j , we have

$$\eta_j \leq f_j - \frac{1}{\sigma_{N_j}^2} (1 - e^{-2r_j}) = \frac{f_{j+1}}{1 + \sigma_{Z_{j+1}}^2 f_{j+1}},$$

from which we have

$$\frac{1}{1 - \sigma_{Z_{j+1}}^2 \eta_j} \leq 1 + \sigma_{Z_{j+1}}^2 f_{j+1} \leq 1 + \sigma_{Z_{j+1}}^2 f_{j+1}^*. \quad (57)$$

From (56) and (57), we have

$$\begin{aligned} \frac{1}{2} \log \frac{G(s_l)}{G(r_l)} &\geq -(s_l - r_l) \sum_{k=l}^{L^*} \frac{\sigma_{Z_{k+1}}^2}{\sigma_{N_l}^2} \left(1 + \sigma_{Z_{k+1}}^2 f_k^*\right) \\ &\quad \times \prod_{j=l+1}^k \left(1 + \sigma_{Z_j}^2 f_j^*\right)^2. \end{aligned} \quad (58)$$

If

$$\sum_{k=l}^{L-2} \frac{\sigma_{Z_{k+1}}^2}{\sigma_{N_l}^2} \left(1 + \sigma_{Z_{k+1}}^2 f_{k+1}^*\right) \prod_{j=l+1}^k \left(1 + \sigma_{Z_j}^2 f_j^*\right)^2 \leq 1 \quad (59)$$

hold for $l = 1, 2, \dots, L-2$, then, by (58), we have

$$\frac{1}{2} \log \frac{G(s_l)}{G(r_l)} \geq -(s_l - r_l)$$

or equivalent to

$$s_l + \frac{1}{2} \log G(s_l) \geq r_l + \frac{1}{2} \log G(r_l)$$

for $l = 1, 2, \dots, L-2$. Hence, (59) is a sufficient condition for the MI condition. ■

B. Proof of $\mathcal{R}_L(D) \subseteq \mathcal{R}_L^{(\text{out})}(D)$

In this appendix we prove $\mathcal{R}_L(D) \subseteq \mathcal{R}_L^{(\text{out})}(D)$ stated in Theorem 2. We first present a lemma necessary for the proof of this inclusion.

Lemma 6:

$$I(\mathbf{X}_0; \hat{\mathbf{X}}_0) \geq \frac{n}{2} \log \left(\frac{\sigma_{\mathbf{X}_0}^2}{\Delta(\mathbf{X}_0, \hat{\mathbf{X}}_0)} \right).$$

Proof: See the proof of Lemma 1 in Oohama [7]. ■

Next, we present an important lemma which is a mathematical core of the converse coding theorem. Let the encoded outputs of $\mathbf{X}_i, i = 0, 1, \dots, L$ by encoder functions φ_i be denoted by $\varphi_i(\mathbf{X}_i) = \mathbf{W}_i$. Set

$$\begin{aligned} r_0 &\triangleq \frac{1}{n} I(\mathbf{X}_0; \mathbf{W}_0 | \mathbf{W}^L), \\ r_i &\triangleq \frac{1}{n} I(\mathbf{X}_i; \mathbf{W}_i | \mathbf{Y}^{L-1}) \\ &= \begin{cases} \frac{1}{n} I(\mathbf{X}_i; \mathbf{W}_i | \mathbf{Y}_i), & \text{for } 1 \leq i \leq L-1, \\ \frac{1}{n} I(\mathbf{X}_L; \mathbf{W}_L | \mathbf{Y}_{L-1}), & \text{for } i = L, \end{cases} \\ \xi &\triangleq \sigma_{\mathbf{X}_0}^2 e^{-\frac{2}{n} I(\mathbf{X}_0; \mathbf{W}_0 | \mathbf{W}^L)}. \end{aligned}$$

Then, we have the following lemma.

Lemma 7:

$$I(\mathbf{X}_0; \mathbf{W}^L) \leq \frac{n}{2} \log [1 + \sigma_{\mathbf{X}_0}^2 f_0(r^L)].$$

For $1 \leq l \leq L-1$, we have

$$\begin{aligned} &\frac{n}{2} \log [1 + \sigma_{\mathbf{Z}_l}^2 g_l(r_0, r^{L-1}, \xi)] \\ &\leq I(\mathbf{Y}_l; \mathbf{W}_l^L | \mathbf{Y}_{l-1}) \leq \frac{n}{2} \log [1 + \sigma_{\mathbf{Z}_l}^2 f_l(r_l^L)]. \end{aligned}$$

From the above lemma we immediately obtain the following.

Lemma 8:

$$\begin{aligned} I(\mathbf{X}_0; \mathbf{W}_S) &\leq \frac{n}{2} \log [1 + \sigma_{\mathbf{X}_0}^2 f_0(r_S)], \\ I(\mathbf{Y}^{L-1}; \mathbf{W}_S | \mathbf{X}_0) &\leq \frac{n}{2} \log F(r_S), \quad S \subseteq \Lambda, \\ I(\mathbf{Y}^{L-1}; \mathbf{W}^L | \mathbf{X}_0) &\geq \frac{n}{2} \log G(\xi, r_0, r^{L-2}). \end{aligned}$$

We prove $\mathcal{R}_L(D) \subseteq \mathcal{R}_L^{(\text{out})}(D)$ by Lemmas 6 and 8 and standard arguments for the proof of the converse coding theorem.

Proof of $\mathcal{R}_L(D) \subseteq \mathcal{R}_L^{(\text{out})}(D)$: We first observe that by virtue of the TS condition,

$$\mathbf{W}_S \rightarrow \mathbf{X}_S \rightarrow (\mathbf{X}_0, \mathbf{Z}^{L-1}) \rightarrow \mathbf{X}_{S^c} \rightarrow \mathbf{W}_{S^c} \quad (60)$$

hold for any subset S of Λ . Assume $(R_0, R_1, \dots, R_L) \in \mathcal{R}_L(D)$. Then, for any $\delta > 0$, there exists an integer $n_0(\delta)$ such that for $n \geq n_0(\delta)$ and for $i \in \Lambda$, we obtain the following chain of inequalities:

$$\begin{aligned} n(R_0 + \delta) &\geq \log M_0 \geq H(\mathbf{W}_0) \geq H(\mathbf{W}_0 | \mathbf{W}^L) \\ &= I(\mathbf{X}_0; \mathbf{W}_0 | \mathbf{W}^L) = nr_0. \end{aligned} \quad (61)$$

Furthermore, for any subset $S \subseteq \Lambda$, we obtain

$$\begin{aligned} &nr_0 + \sum_{i \in S} n(R_i + \delta) \\ &\geq I(\mathbf{X}_0; \mathbf{W}_0 | \mathbf{W}^L) + \sum_{i \in S} H(\mathbf{W}_i) \\ &= H(\mathbf{W}_0 | \mathbf{W}^L) + \sum_{i \in S} H(\mathbf{W}_i) \\ &\geq H(\mathbf{W}_0 | \mathbf{W}_S \mathbf{W}_{S^c}) + H(\mathbf{W}_S | \mathbf{W}_{S^c}) = H(\mathbf{W}_0 \mathbf{W}_S | \mathbf{W}_{S^c}) \\ &= I(\mathbf{X}_0 \mathbf{Z}^{L-1}; \mathbf{W}_0 \mathbf{W}_S | \mathbf{W}_{S^c}) \\ &\quad + H(\mathbf{W}_0 \mathbf{W}_S | \mathbf{W}_{S^c} \mathbf{X}_0 \mathbf{Z}^{L-1}) \\ &\stackrel{(a)}{=} I(\mathbf{X}_0 \mathbf{Z}^{L-1}; \mathbf{W}_0 \mathbf{W}_S | \mathbf{W}_{S^c}) + \sum_{i \in S} H(\mathbf{W}_i | \mathbf{X}_0 \mathbf{Z}^{L-1}) \\ &= I(\mathbf{X}_0 \mathbf{Y}^{L-1}; \mathbf{W}_0 \mathbf{W}_S | \mathbf{W}_{S^c}) + \sum_{i \in S} I(\mathbf{X}_i; \mathbf{W}_i | \mathbf{Y}^{L-1}). \end{aligned} \quad (62)$$

Step (a) follows from (60). On the other hand, by Lemma 6, we have for $n \geq n_0(\delta)$,

$$\begin{aligned} I(\mathbf{X}_0; \mathbf{W}_0 | \mathbf{W}^L) &= \frac{n}{2} \log \left(\frac{\sigma_{\mathbf{X}_0}^2}{\xi} \right) \\ &\geq I(\mathbf{X}_0; \hat{\mathbf{X}}_0) \geq \frac{n}{2} \log \left(\frac{\sigma_{\mathbf{X}_0}^2}{D + \delta} \right), \end{aligned}$$

which together with (61), (62), and Lemma 8 yields the following lower bounds of $I(\mathbf{X}_0; \mathbf{W}_0 | \mathbf{W}^L)$ and $I(\mathbf{X}_0 \mathbf{Y}^{L-1}; \mathbf{W}_0 \mathbf{W}_S | \mathbf{W}_{S^c})$:

$$\begin{aligned} I(\mathbf{X}_0; \mathbf{W}_0 | \mathbf{W}^L) &= I(\mathbf{X}_0; \mathbf{W}_0 \mathbf{W}^L) - I(\mathbf{X}_0; \mathbf{W}^L) \\ &\geq \frac{n}{2} \log \left[\frac{\sigma_{\mathbf{X}_0}^2}{\{1 + \sigma_{\mathbf{X}_0}^2 f_0(r^L)\} \xi} \right] \\ &\geq \frac{n}{2} \log \left[\frac{\sigma_{\mathbf{X}_0}^2}{\{1 + \sigma_{\mathbf{X}_0}^2 f_0(r^L)\} (D + \delta)} \right], \\ I(\mathbf{X}_0 \mathbf{Y}^{L-1}; \mathbf{W}_0 \mathbf{W}_S | \mathbf{W}_{S^c}) &= I(\mathbf{X}_0 \mathbf{Y}^{L-1}; \mathbf{W}_0 \mathbf{W}_S \mathbf{W}_{S^c}) - I(\mathbf{X}_0 \mathbf{Y}^{L-1}; \mathbf{W}_{S^c}) \\ &= I(\mathbf{X}_0; \mathbf{W}_0 \mathbf{W}^L) + I(\mathbf{Y}^{L-1}; \mathbf{W}^L | \mathbf{X}_0) \\ &\quad - I(\mathbf{X}_0; \mathbf{W}_{S^c}) - I(\mathbf{Y}^{L-1}; \mathbf{W}_{S^c} | \mathbf{X}_0) \\ &\geq \frac{n}{2} \log \left[\frac{\sigma_{\mathbf{X}_0}^2 G(\xi, r_0, r^{L-2})}{F(r_{S^c}) \{1 + \sigma_{\mathbf{X}_0}^2 f_0(r_{S^c})\} \xi} \right] \\ &\geq \frac{n}{2} \log \left[\frac{\sigma_{\mathbf{X}_0}^2 G(D + \delta, r_0, r^{L-2})}{F(r_{S^c}) \{1 + \sigma_{\mathbf{X}_0}^2 f_0(r_{S^c})\} (D + \delta)} \right]. \end{aligned} \quad (63)$$

From (62) and (64), we have

$$\begin{aligned} \sum_{i \in S} (R_i + \delta) &\geq \frac{1}{2} \log \left[\frac{\sigma_{\mathbf{X}_0}^2 G(D + \delta, r_0, r^{L-2})}{F(r_{S^c}) (D + \delta) \{1 + \sigma_{\mathbf{X}_0}^2 f_0(r_{S^c})\}} \right] \\ &\quad + \sum_{i \in S} r_i - r_0. \end{aligned} \quad (65)$$

Note here that $\sum_{i \in S} (R_i + \delta)$ are nonnegative. Hence, from (61), (63) and (65), we obtain

$$R_0 + \delta \geq r_0 \geq \frac{1}{2} \log \left[\frac{\sigma_{X_0}^2}{\{1 + \sigma_{X_0}^2 f_0(r^L)\}^{(D+\delta)}} \right] \quad (66)$$

and for $S \subseteq \Lambda$

$$\sum_{i \in S} (R_i + \delta) \geq J_S(D + \delta, r_0, r^{L-2}, r_S | r_{S^c}).$$

The inequality (66) implies that $r_0^L \in \mathcal{B}_L(D + \delta)$. Thus, by letting $\delta \rightarrow 0$, we obtain $(R_0, R_1, \dots, R_L) \in \mathcal{R}_L^{(\text{out})}(D)$. ■

Finally, we prove Lemma 7. For n dimensional random vector $\mathbf{U}$ with density, let $h(\mathbf{U})$ be a differential entropy of $\mathbf{U}$. The following two lemmas are some variants of the entropy power inequality.

Lemma 9: Let $\mathbf{U}_i, i = 1, 2, 3$ be n dimensional random vectors with densities and let T be a random variable taking values in a finite set. We assume that $\mathbf{U}_3$ is independent of $\mathbf{U}_1, \mathbf{U}_2$, and T . Then, we have

$$\frac{1}{2\pi e} e^{\frac{2}{n} h(\mathbf{U}_2 + \mathbf{U}_3 | \mathbf{U}_1 T)} \geq \frac{1}{2\pi e} e^{\frac{2}{n} h(\mathbf{U}_2 | \mathbf{U}_1 T)} + \frac{1}{2\pi e} e^{\frac{2}{n} h(\mathbf{U}_3)}.$$

Lemma 10: Let $\mathbf{U}_i, i = 1, 2, 3$ be n random vectors with densities. Let T_1, T_2 be random variables taking values in finite sets. We assume that those five random variables form a Markov chain $T_1 \rightarrow \mathbf{U}_1 \rightarrow \mathbf{U}_3 \rightarrow \mathbf{U}_2 \rightarrow T_2$ in this order. Then, we have

$$\begin{aligned} & \frac{1}{2\pi e} e^{\frac{2}{n} h(\mathbf{U}_1 + \mathbf{U}_2 | \mathbf{U}_3 T_1 T_2)} \\ & \geq \frac{1}{2\pi e} e^{\frac{2}{n} h(\mathbf{U}_1 | \mathbf{U}_3 T_1)} + \frac{1}{2\pi e} e^{\frac{2}{n} h(\mathbf{U}_2 | \mathbf{U}_3 T_2)}. \end{aligned}$$

Proof of Lemma 7: Define the sequence of n dimensional random vectors $\{\mathbf{S}_l\}_{l=1}^{L-1}$ by

$$\mathbf{S}_l = \frac{1}{\sigma_{Z_l}^2} \mathbf{X}_l + \frac{1}{\sigma_{Z_{l+1}}^2} \mathbf{Y}_{l+1}, \quad 1 \leq l \leq L-1. \quad (67)$$

By an elementary computation, we obtain

$$\left. \begin{aligned} \mathbf{X}_0 &= \frac{\sigma_{\hat{N}_0}^2}{\sigma_{Z_1}^2} \mathbf{Y}_1 + \hat{N}_0, \\ \mathbf{Y}_l &= \frac{\sigma_{\hat{N}_l}^2}{\sigma_{Z_l}^2} \mathbf{Y}_{l-1} + \sigma_{Z_l}^2 \mathbf{S}_l + \hat{N}_l, \quad 1 \leq l \leq L-1. \end{aligned} \right\} \quad (68)$$

where $\hat{N}_l, 0 \leq l \leq L-1$ is an n dimensional random vector whose components are n independent copies of a Gaussian random variable with mean 0 and variance $\sigma_{\hat{N}_l}^2$. $\hat{N}_0$ is independent of $\mathbf{Y}_1$. For each $1 \leq l \leq L-1$, $\hat{N}_l$ is independent of $\mathbf{Y}_{l-1}$ and $\mathbf{S}_l$. The variance $\sigma_{\hat{N}_l}^2, 0 \leq l \leq L-1$ have the following form:

$$\left. \begin{aligned} \frac{1}{\sigma_{\hat{N}_0}^2} &= \frac{1}{\sigma_{X_0}^2} + \frac{1}{\sigma_{Z_1}^2}, \\ \frac{1}{\sigma_{\hat{N}_l}^2} &= \frac{1}{\sigma_{Z_l}^2} + \frac{1}{\sigma_{Z_{l+1}}^2} + \frac{1}{\sigma_{Z_{l+1}}^2}, \quad 1 \leq l \leq L-1. \end{aligned} \right\} \quad (69)$$

Set

$$\begin{aligned} \lambda_0 &\triangleq \frac{1}{2\pi e} e^{\frac{2}{n} h(\mathbf{X}_0 | W^L)}, \quad \tilde{\mu}_0 \triangleq \frac{1}{2\pi e} e^{\frac{2}{n} h(\mathbf{Y}_1 | W^L)}, \\ \mu_0 &\triangleq \frac{1}{2\pi e} e^{\frac{2}{n} h(\mathbf{Y}_1 | \mathbf{X}_0 W^L)}, \\ \lambda_l &\triangleq \frac{1}{2\pi e} e^{\frac{2}{n} h(\mathbf{Y}_l | \mathbf{Y}_{l-1} W_l^L)}, \quad 1 \leq l \leq L, \\ \tilde{\mu}_l &\triangleq \frac{1}{2\pi e} e^{\frac{2}{n} h(\mathbf{S}_l | \mathbf{Y}_{l-1} W_l^L)}, \quad \mu_l \triangleq \frac{1}{2\pi e} e^{\frac{2}{n} h(\mathbf{S}_l | \mathbf{Y}_l W_l^L)}, \\ &1 \leq l \leq L-1. \end{aligned}$$

We can easily verify that

$$\tilde{\mu}_0 = \mu_0 \lambda_0 \frac{1}{\sigma_{\hat{N}_0}^2}, \quad \tilde{\mu}_l = \mu_l \lambda_l \frac{1}{\sigma_{\hat{N}_l}^2}, \quad 1 \leq l \leq L-1. \quad (70)$$

Applying Lemma 9 to (68), we obtain

$$\left. \begin{aligned} \lambda_0 &\geq \frac{\sigma_{\hat{N}_0}^4}{\sigma_{Z_1}^4} \tilde{\mu}_0 + \sigma_{\hat{N}_0}^2, \\ \lambda_l &\geq \sigma_{\hat{N}_l}^4 \tilde{\mu}_l + \sigma_{\hat{N}_l}^2, \quad 1 \leq l \leq L-1. \end{aligned} \right\} \quad (71)$$

From (70) and (71), we obtain

$$\left. \begin{aligned} \lambda_0^{-1} &\leq \frac{1}{\sigma_{X_0}^2} + \frac{1}{\sigma_{Z_1}^2} \left(1 - \frac{\lambda_1}{\sigma_{Z_1}^2} \right), \\ \lambda_l^{-1} &\leq \frac{1}{\sigma_{Z_l}^2} + \frac{1}{\sigma_{Z_{l+1}}^2} - \mu_l, \quad 1 \leq l \leq L-1. \end{aligned} \right\} \quad (72)$$

On the other hand, we note that for each $1 \leq l \leq L-1$, the five random variables $W_l, \mathbf{X}_l, \mathbf{Y}_l, \mathbf{Y}_{l+1}$, and W_{l+1}^L form a Markov chain $W_l \rightarrow \mathbf{X}_l \rightarrow \mathbf{Y}_l \rightarrow \mathbf{Y}_{l+1} \rightarrow W_{l+1}^L$ in this order. Then, applying Lemma 10 to (67), we obtain

$$\mu_l \geq \frac{1}{\sigma_{Z_l}^2} e^{-2r_l} + \frac{1}{\sigma_{Z_{l+1}}^2} \lambda_{l+1}, \quad 1 \leq l \leq L-1. \quad (73)$$

Combining (72) and (73), we obtain for $1 \leq l \leq L-1$,

$$\lambda_l^{-1} \leq \frac{1}{\sigma_{Z_l}^2} + \frac{1}{\sigma_{Z_{l+1}}^2} (1 - e^{-2r_l}) + \frac{1}{\sigma_{Z_{l+1}}^2} \left(1 - \frac{\lambda_{l+1}}{\sigma_{Z_{l+1}}^2} \right). \quad (74)$$

Set $\nu_0 \triangleq \lambda_0^{-1} - \frac{1}{\sigma_{X_0}^2}$, $\nu_l \triangleq \lambda_l^{-1} - \frac{1}{\sigma_{Z_l}^2}$, $1 \leq l \leq L-1$. Then, we have

$$I(\mathbf{X}_0, W^L) = \frac{n}{2} \log(1 + \sigma_{X_0}^2 \nu_0),$$

$$I(\mathbf{Y}_l, W_l^L | \mathbf{Y}_{l-1}) = \frac{n}{2} \log(1 + \sigma_{Z_l}^2 \nu_l), \quad 1 \leq l \leq L-1,$$

$$I(\mathbf{Y}_L, W_L | \mathbf{Y}_{L-1}) = \frac{n}{2} \log(1 + \sigma_{Z_L}^2 \nu_L) = n r_L$$

Note that $\nu_l, 0 \leq l \leq L-1$ are nonnegative. From (72) and (74), $\{\nu_l\}_{l=0}^L$ satisfies the following recursion:

$$\nu_L = \frac{1}{\sigma_{Z_L}^2} (e^{2r_L} - 1), \quad (75)$$

$$\begin{aligned} \nu_{L-1} &\leq \frac{\nu_L}{1 + \sigma_{Z_L}^2 \nu_L} + \frac{1 - e^{-2r_{L-1}}}{\sigma_{Z_{L-1}}^2} \\ &= \frac{1 - e^{-2r_L}}{\sigma_{Z_L}^2} + \frac{1 - e^{-2r_{L-1}}}{\sigma_{Z_{L-1}}^2} \end{aligned} \quad (76)$$

$$\nu_l \leq \frac{\nu_{l+1}}{1 + \sigma_{Z_{l+1}}^2 \nu_{l+1}} + \frac{1 - e^{-2r_l}}{\sigma_{Z_l}^2}, \quad L-2 \geq l \geq 1, \quad (77)$$

$$\nu_0 \leq \frac{\nu_1}{1 + \sigma_{Z_1}^2 \nu_1}, \quad \nu_0 = \frac{e^{-2r_0}}{\xi} - \frac{1}{\sigma_{X_0}^2}. \quad (78)$$

From (75)-(78), we obtain the upper bounds of $I(\mathbf{X}_0; W^L)$ and $I(\mathbf{Y}_l; W_l^L | \mathbf{Y}_{l-1})$, $1 \leq l \leq L-1$ in Lemma 7. On the other hand, from (77), (78), and the nonnegative property of $\nu_l, 0 \leq l \leq L-1$, we have

$$\nu_0 = \left[\frac{e^{-2r_0}}{\xi} - \frac{1}{\sigma_{X_0}^2} \right]^+, \quad \nu_1 \geq \frac{\nu_0}{1 - \sigma_{Z_1}^2 \nu_0}, \quad (79)$$

$$\nu_{l+1} \geq \frac{\left[\nu_l - \frac{1}{\sigma_{Z_l}^2} (1 - e^{-2r_l}) \right]^+}{1 - \sigma_{Z_{l+1}}^2 \left[\nu_l - \frac{1}{\sigma_{Z_l}^2} (1 - e^{-2r_l}) \right]^+}, \quad 1 \leq l \leq L-1. \quad (80)$$

From (79) and (80), we obtain the lower bound of $I(\mathbf{Y}_l; W_l^L | \mathbf{Y}_{l-1})$, $1 \leq l \leq L-1$ in Lemma 7. ■

C. Proof of Lemma 3

Let $\alpha_2^L, \beta_2^L \in \mathcal{A}_L(\alpha_1)$. Then, we have the following chain of inequalities:

$$\begin{aligned}
& t\zeta(\alpha_2^L) + (1-t)\zeta(\beta_2^L) \\
&= \sum_{l=1}^{L-1} \left\{ t \log \left(1 - \frac{\alpha_l}{1-\epsilon\alpha_l} + \frac{\alpha_{l+1}}{\tau_{l+1}} \right) \right. \\
&\quad \left. + (1-t) \log \left(1 - \frac{\beta_l}{1-\epsilon\beta_l} + \frac{\beta_{l+1}}{\tau_{l+1}} \right) \right\} \\
&\quad + \sum_{l=1}^{L-1} \{ t \log(1-\epsilon\alpha_l) + (1-t) \log(1-\epsilon\beta_l) \} \\
&\quad + t \log(1-\alpha_L) + (1-t) \log(1-\beta_L) \\
&\stackrel{(a)}{\leq} \sum_{l=1}^{L-1} \log \left\{ 1 - t \frac{\alpha_l}{1-\epsilon\alpha_l} + t \frac{\alpha_{l+1}}{\tau_{l+1}} \right. \\
&\quad \left. - (1-t) \frac{\beta_l}{1-\epsilon\beta_l} + (1-t) \frac{\beta_{l+1}}{\tau_{l+1}} \right\} \\
&\quad + \sum_{l=1}^{L-1} \log \{ 1 - \epsilon[t\alpha_l + (1-t)\beta_l] \} \\
&\quad + \log \{ 1 - [t\alpha_L + (1-t)\beta_L] \} \\
&\stackrel{(b)}{\leq} \sum_{l=1}^{L-1} \log \left\{ 1 - \frac{t\alpha_l + (1-t)\beta_l}{1-\epsilon[t\alpha_l + (1-t)\beta_l]} \right. \\
&\quad \left. + \frac{t\alpha_{l+1} + (1-t)\beta_{l+1}}{\tau_{l+1}} \right\} \\
&\quad + \sum_{l=1}^{L-1} \log \{ 1 - \epsilon[t\alpha_l + (1-t)\beta_l] \} \\
&\quad + \log \{ 1 - [t\alpha_L + (1-t)\beta_L] \} \\
&= \zeta(t\alpha_2^L + (1-t)\beta_2^L).
\end{aligned}$$

Step (a) follows from the strict concavity of the logarithm function. Step (b) follows from the strict concavity of $\frac{-a}{1-\epsilon a}$ for $a > 0$. ■

D. Proof of Lemma 4

Proof of Lemma 4 part a): For the proof we use the following inequality:

$$\frac{1+a}{1+\epsilon(1+a)} - \frac{a}{1+\epsilon a} \leq \frac{1}{1+\epsilon}. \quad (81)$$

The recursion of (15) is equivalent to

$$\frac{\tau_l \theta_{l-1}(\omega)}{1-\epsilon_{l-1}\theta_{l-1}(\omega)} = 2\theta_l - \frac{1 + \frac{\theta_{l+1}(\omega)}{\tau_{l+1}}}{1+\epsilon_l \left[1 + \frac{\theta_{l+1}(\omega)}{\tau_{l+1}} \right]} + \tau_l \quad (82)$$

for $L-1 \geq l \geq 2$. Applying (81) to the second term in the right members of (82) and considering the assumption $\tau_l \geq \frac{1}{1+\epsilon_l}$ for $L-1 \geq l \geq 2$, we have

$$\frac{\tau_l \theta_{l-1}(\omega)}{1-\epsilon_{l-1}\theta_{l-1}(\omega)} \geq 2\theta_l(\omega) - \frac{\frac{\theta_{l+1}(\omega)}{\tau_{l+1}}}{1+\epsilon_l \frac{\theta_{l+1}(\omega)}{\tau_{l+1}}}$$

or equivalent to

$$\frac{\theta_{l-1}(\omega)}{1+\epsilon_{l-1}\theta_{l-1}(\omega)} - \theta_l(\omega) \geq \theta_l(\omega) - \frac{\frac{\theta_{l+1}(\omega)}{\tau_{l+1}}}{1+\epsilon_l \frac{\theta_{l+1}(\omega)}{\tau_{l+1}}} \quad (83)$$

for $L-1 \geq l \geq 2$. We first prove (17) for $l = L$. The equation

$$\theta_{L-1}(\omega) = \frac{\frac{2\theta_L(\omega)-1}{\tau_L} + 1}{1+\epsilon_{L-1} \left[\frac{2\theta_L(\omega)-1}{\tau_L} + 1 \right]} \quad (84)$$

is equivalent to

$$\tau_L \left(\frac{\theta_{L-1}(\omega)}{1-\epsilon_{L-1}\theta_{L-1}(\omega)} - 1 \right) - \theta_L(\omega) = \theta_L(\omega) - 1. \quad (85)$$

It is obvious that

$$0 \leq \theta_L(\omega) = \omega < 1 = \epsilon_L^{-1}. \quad (86)$$

From (85) and (86), we have

$$\tau_L \left(\frac{\theta_{L-1}(\omega)}{1-\epsilon_{L-1}\theta_{L-1}(\omega)} - 1 \right) < \theta_L(\omega).$$

From (85) and $\tau_L \geq 1$, we have

$$\theta_L(\omega) \leq \frac{\frac{1}{2}\tau_L\theta_{L-1}(\omega)}{1-\epsilon_{L-1}\theta_{L-1}(\omega)} \leq \frac{\tau_L\theta_{L-1}(\omega)}{1-\epsilon_{L-1}\theta_{L-1}(\omega)}.$$

Thus, (17) holds for $l = L$. We assume that (17) holds for some $l+1$ with $L \geq l+1$, that is,

$$0 \leq \theta_{l+1}(\omega) \leq \frac{\tau_{l+1}\theta_l(\omega)}{1-\epsilon_l\theta_l(\omega)}, \quad \tau_{l+1} \left(\frac{\theta_l(\omega)}{1-\epsilon_l\theta_l(\omega)} - 1 \right) < \theta_{l+1}(\omega) < \epsilon_{l+1}^{-1}. \quad (87)$$

From (87), we obtain

$$\left. \begin{aligned} \epsilon_l^{-1} &> \theta_l(\omega) \geq \frac{\frac{\theta_{l+1}(\omega)}{\tau_{l+1}}}{1+\epsilon_l \frac{\theta_{l+1}(\omega)}{\tau_{l+1}}} > 0, \\ \theta_l(\omega) &< \frac{1 + \frac{\theta_{l+1}(\omega)}{\tau_{l+1}}}{1+\epsilon_l \left(1 + \frac{\theta_{l+1}(\omega)}{\tau_{l+1}} \right)}. \end{aligned} \right\} \quad (88)$$

Using (82), we have

$$\begin{aligned} & \frac{\tau_l \theta_{l-1}(\omega)}{1-\epsilon_{l-1}\theta_{l-1}(\omega)} - \theta_l(\omega) \\ &= \theta_l(\omega) - \frac{1 + \frac{\theta_{l+1}(\omega)}{\tau_{l+1}}}{1+\epsilon_l \left(1 + \frac{\theta_{l+1}(\omega)}{\tau_{l+1}} \right)} + \tau_l \stackrel{(a)}{<} \tau_l. \end{aligned}$$

Step (a) follows from the second inequality of (88). Using (83), we have

$$\frac{\tau_l \theta_{l-1}(\omega)}{1-\epsilon_{l-1}\theta_{l-1}(\omega)} - \theta_l(\omega) \geq \theta_l(\omega) - \frac{\frac{\theta_{l+1}(\omega)}{\tau_{l+1}}}{1+\epsilon_l \frac{\theta_{l+1}(\omega)}{\tau_{l+1}}} \stackrel{(a)}{\geq} 0.$$

Step (a) follows from the first inequality of (88). Thus, (17) holds for l , completing the proof. ■

Proof of Lemma 4 part b): We first observe that

$$\begin{aligned}
& \zeta(\alpha_2^L) \\
&= \sum_{l=1}^{L-1} \left\{ \log \left(1 - \frac{\alpha_l}{1 - \epsilon_l \alpha_l} + \frac{\alpha_{l+1}}{\tau_{l+1}} \right) + \log(1 - \epsilon_l \alpha_l) \right\} \\
&\quad + \log(1 - \alpha_L) \\
&= \sum_{l=2}^L \log \left\{ 1 - \epsilon_{l-1} \alpha_{l-1} - \alpha_{l-1} + (1 - \epsilon_{l-1} \alpha_{l-1}) \frac{\alpha_l}{\tau_l} \right\} \\
&\quad + \log(1 - \alpha_L) \\
&= \sum_{l=1}^{L-1} \log \left[1 + \frac{\alpha_{l+1}}{\tau_{l+1}} - \left\{ 1 + \epsilon_l \left(1 + \frac{\alpha_{l+1}}{\tau_{l+1}} \right) \right\} \alpha_l \right] \\
&\quad + \log(1 - \alpha_L).
\end{aligned}$$

Computing $\frac{\partial}{\partial \alpha_l} \zeta(\alpha_2^L)$ we obtain

$$\left. \begin{aligned} \frac{\partial}{\partial \alpha_L} \zeta(\alpha_2^L) &= \frac{1}{\alpha_L - \tau_L \left(\frac{\alpha_{L-1}}{1 - \epsilon_{L-1} \alpha_{L-1}} - 1 \right)} - \frac{1}{1 - \alpha_L}, \\ \frac{\partial}{\partial \alpha_l} \zeta(\alpha_2^L) &= \frac{1}{\alpha_l - \tau_l \left(\frac{\alpha_{l-1}}{1 - \epsilon_{l-1} \alpha_{l-1}} - 1 \right)} - \frac{1 + \frac{\alpha_{l+1}}{\tau_{l+1}}}{1 + \epsilon_l \left[1 + \frac{\alpha_{l+1}}{\tau_{l+1}} \right]} - \alpha_l \end{aligned} \right\} \quad \text{for } L-1 \geq l \geq 2. \quad (89)$$

From (89), when $\nabla \zeta(\alpha_2^L) = \mathbf{0}$, α_2^L must satisfy

$$\left. \begin{aligned} -2\alpha_L + 1 + \tau_L \left(\frac{\alpha_{L-1}}{1 - \epsilon_{L-1} \alpha_{L-1}} - 1 \right) &= 0, \\ \frac{1 + \frac{\alpha_{l+1}}{\tau_{l+1}}}{1 + \epsilon_l \left[1 + \frac{\alpha_{l+1}}{\tau_{l+1}} \right]} - 2\alpha_l + \tau_l \left(\frac{\alpha_{l-1}}{1 - \epsilon_{l-1} \alpha_{l-1}} - 1 \right) &= 0, \end{aligned} \right\} \quad \text{for } L-1 \geq l \geq 2. \quad (90)$$

From (90), we obtain

$$\left. \begin{aligned} \alpha_{L-1} &= \frac{\frac{2\alpha_L - 1}{\tau_L} + 1}{1 + \epsilon_{L-1} \left[\frac{2\alpha_L - 1}{\tau_L} + 1 \right]}, \\ \alpha_{l-1} &= \frac{\frac{1}{\tau_l} \left[2\alpha_l - \frac{1 + \frac{\alpha_{l+1}}{\tau_{l+1}}}{1 + \epsilon_l \left(1 + \frac{\alpha_{l+1}}{\tau_{l+1}} \right)} + \tau_l \right]}{1 + \frac{\epsilon_{l-1}}{\tau_l} \left[2\alpha_l - \frac{1 + \frac{\alpha_{l+1}}{\tau_{l+1}}}{1 + \epsilon_l \left(1 + \frac{\alpha_{l+1}}{\tau_{l+1}} \right)} + \tau_l \right]} \end{aligned} \right\} \quad \text{for } L-1 \geq l \geq 2. \quad (91)$$

The relation (91) implies that $\nabla \zeta|_{\alpha_2^L = \theta_2^L(\omega)} = \mathbf{0}$. ■

Proof of Lemma 4 part c): For the proof we use the following recursion:

$$\frac{\tau_l \theta_{l-1}(\omega)}{1 - \epsilon_l \theta_{l-1}(\omega)} = 2\theta_l(\omega) - \frac{1 + \theta_{l-1}(\omega)}{1 + \epsilon_l [1 + \theta_{l+1}(\omega)]} + 1. \quad (92)$$

Taking the derivative of both sides of (92) with respect to ω , we obtain

$$\begin{aligned} & \frac{1}{(1 - \epsilon_{l-1} \theta_{l-1}(\omega))^2} \frac{d\theta_{l-1}}{d\omega} \cdot \tau_l \\ &= 2 \frac{d\theta_l}{d\omega} - \frac{1}{\{1 + \epsilon_l (\theta_{l+1}(\omega) + 1)\}^2} \frac{d\theta_{l+1}}{d\omega} \cdot \tau_{l+1}^{-1}. \end{aligned} \quad (93)$$

Since $\theta_2^L(\omega) \in \mathcal{A}_L(\theta_1(\omega))$, we have

$$\tau_l \left(\frac{\theta_{l-1}(\omega)}{1 - \epsilon_{l-1} \theta_{l-1}(\omega)} - 1 \right) < \theta_l(\omega).$$

The above inequality is equivalent to

$$1 + \epsilon_{l-1} \left(\frac{\theta_l(\omega)}{\tau_l} + 1 \right) > \frac{1}{1 - \epsilon_{l-1} \theta_{l-1}(\omega)}. \quad (94)$$

From (93) and (94) we have

$$\begin{aligned} & \left\{ 1 + \epsilon_{l-1} \left(\frac{\theta_l(\omega)}{\tau_l} + 1 \right) \right\}^2 \frac{d\theta_{l-1}}{d\omega} \cdot \tau_l \\ & \geq 2 \frac{d\theta_l}{d\omega} - \frac{1}{\left\{ 1 + \epsilon_l \left(\frac{\theta_{l+1}(\omega)}{\tau_{l+1}} + 1 \right) \right\}^2} \frac{d\theta_{l+1}}{d\omega} \cdot \tau_{l+1}^{-1}. \end{aligned} \quad (95)$$

The above inequality is equivalent to

$$\begin{aligned} & \left\{ 1 + \epsilon_{l-1} \left(\frac{\theta_l(\omega)}{\tau_l} + 1 \right) \right\}^2 \left(\frac{1}{\sigma_{l-1}^2} \frac{d\theta_{l-1}}{d\omega} \right) \\ & \geq 2 \left(\frac{1}{\sigma_l^2} \frac{d\theta_l}{d\omega} \right) - \frac{1}{\left\{ 1 + \epsilon_l \left(\frac{\theta_{l+1}(\omega)}{\tau_{l+1}} + 1 \right) \right\}^2} \\ & \quad \times \left(\frac{1}{\sigma_{l+1}^2} \frac{d\theta_{l+1}}{d\omega} \right) \end{aligned} \quad (96)$$

For $1 \leq l \leq L$, set

$$\Phi_l(\omega) \triangleq \left(\frac{1}{\sigma_l^2} \frac{d\theta_l}{d\omega} \right) \prod_{j=2}^l \frac{1}{\left\{ 1 + \epsilon_{j-1} \left(\frac{\theta_j(\omega)}{\tau_j} + 1 \right) \right\}^2}.$$

Then, by (96), we have

$$\Phi_{l-1}(\omega) \geq 2\Phi_l(\omega) - \Phi_{l+1}(\omega) \quad \text{for } 2 \leq l \leq L-1. \quad (97)$$

From (97) we have

$$\begin{aligned} & \Phi_{l-1}(\omega) - \Phi_l(\omega) \geq \Phi_l(\omega) - \Phi_{l+1}(\omega) \\ & \geq \Phi_{L-1}(\omega) - \Phi_L(\omega) \\ & = \left[\frac{1}{\sigma_{L-1}^2} \cdot \frac{d\theta_{L-1}}{d\omega} - \frac{1}{\sigma_L^2} \cdot \frac{1}{\left\{ 1 + \epsilon_L \left(\frac{\theta_L(\omega)}{\tau_L} + 1 \right) \right\}^2} \right] \\ & \quad \times \prod_{j=2}^{L-1} \frac{1}{\left\{ 1 + \epsilon_{j-1} \left(\frac{\theta_j(\omega)}{\tau_j} + 1 \right) \right\}^2} \\ & = \left[\frac{2}{\left\{ 1 + \epsilon_{L-1} \left(\frac{2\omega-1}{\tau_L} + 1 \right) \right\}^2} - \frac{1}{\left\{ 1 + \epsilon_{L-1} \left(\frac{\omega}{\tau_L} + 1 \right) \right\}^2} \right] \\ & \quad \times \frac{1}{\sigma_L^2} \cdot \prod_{j=2}^{L-1} \frac{1}{\left\{ 1 + \epsilon_{j-1} \left(\frac{\theta_j(\omega)}{\tau_j} + 1 \right) \right\}^2}. \end{aligned} \quad (98)$$

Set

$$\begin{aligned} A(\omega) & \triangleq \left[\frac{2}{\left\{ 1 + \epsilon_{L-1} \left(\frac{2\omega-1}{\tau_L} + 1 \right) \right\}^2} - \frac{1}{\left\{ 1 + \epsilon_{L-1} \left(\frac{\omega}{\tau_L} + 1 \right) \right\}^2} \right] \\ & \quad \times \frac{1}{\sigma_L^2} \cdot \prod_{j=2}^{L-1} \frac{1}{\left\{ 1 + \epsilon_{j-1} \left(\frac{\theta_j(\omega)}{\tau_j} + 1 \right) \right\}^2}. \end{aligned}$$

Then, by (98), we have

$$\begin{aligned}\Phi_l(\omega) &\geq \Phi_L(\omega) + (L-l)A(\omega) \\ &= \left[\frac{2(L-l)}{\left\{1+\epsilon_{L-l-1}\left(\frac{2\omega-1}{\tau_L}+1\right)\right\}^2} - \frac{L-(l+1)}{\left\{1+\epsilon_{L-l-1}\left(\frac{\omega}{\tau_L}+1\right)\right\}^2} \right] \\ &\quad \times \frac{1}{\sigma_L^2} \cdot \prod_{j=2}^{L-1} \frac{1}{\left\{1+\epsilon_{j-1}\left(\frac{\theta_j(\omega)}{\tau_j}+1\right)\right\}^2},\end{aligned}$$

from which we obtain

$$\begin{aligned}\frac{d\theta_l}{d\omega} &\geq \left[\frac{2(L-l)}{\left\{1+\epsilon_{L-l-1}\left(\frac{2\omega-1}{\tau_L}+1\right)\right\}^2} - \frac{L-(l+1)}{\left\{1+\epsilon_{L-l-1}\left(\frac{\omega}{\tau_L}+1\right)\right\}^2} \right] \\ &\quad \times \frac{\sigma_l^2}{\sigma_L^2} \cdot \prod_{j=l+1}^{L-1} \frac{1}{\left\{1+\epsilon_{j-1}\left(\frac{\theta_j(\omega)}{\tau_j}+1\right)\right\}^2},\end{aligned}$$

completing the proof. $\blacksquare$

REFERENCES

- [1] D. Slepian and J. K. Wolf, "Noiseless coding of correlated information sources," *IEEE Trans. Inform. Theory*, vol. IT-19, pp. 471-480, July 1973.
- [2] A. D. Wyner, "On source coding with side information at the decoder," *IEEE Trans. Inform. Theory*, vol. IT-21, pp. 294-300, May 1975.
- [3] R. F. Ahlswede and J. Körner, "Source coding with side information and a converse for degraded broadcast channels," *IEEE Trans. Inform. Theory*, vol. IT-21, pp. 629-637, Nov. 1975.
- [4] J. Körner and K. Marton, "How to encode the module-two sum of binary sources," *IEEE Trans. Inform. Theory*, vol. IT-25, pp. 219-221, Mar. 1979.
- [5] S. I. Gelfand and M. S. Pinsker, "Source coding with incomplete side information," (in Russian) *Probl. Pered. Inform.*, vol. 15, no. 2, pp. 45-57, 1979.
- [6] Y. Oohama, "Gaussian multiterminal source coding," *IEEE Trans. Inform. Theory*, vol. 43, pp. 1912-1923, Nov. 1997.
- [7] Y. Oohama, "The rate-distortion function for the quadratic Gaussian CEO problem," *IEEE Trans. Inform. Theory*, vol. 44, pp. 1057-1070, May 1998.
- [8] Y. Oohama, "Rate-distortion theory for Gaussian multiterminal source coding systems with several side informations at the decoder," *IEEE Trans. Inform. Theory*, vol. 51, pp. 2577-2593, July 2005.
- [9] A. Pandya, A. Kansal, G. Pottie and M. Srivastava, "Lossy source coding of multiple Gaussian sources: m-helper problem" *Proceedings of IEEE Information Theory Workshop, San Antonio, TX*, pp. 34-38, Oct. 2004.
- [10] Y. Oohama, "Gaussian multiterminal source coding with several side informations at the decoder," *Proceedings of IEEE International Symposium on Information Theory*, Seattle, USA, July 9-14, pp. 1409-1413, July 2006.
- [11] S. Tavildar, P. Viswanath, and A. B. Wagner, "The Gaussian many-helper-one distributed source coding problem," *Proceedings of IEEE Information Theory Workshop*, pp. 596-600, Oct. 2006, *preprint*; available at http://arxiv.org/PS_cache/arxiv/pdf/0805/0805.1857v1.pdf.
- [12] T. Berger, "Multiterminal source coding," in *the Information Theory Approach to Communications* (CISM Courses and Lectures, no. 229), G. Longo, Ed. Vienna and New York : Springer-Verlag, 1978, pp. 171-231.
- [13] S. Y. Tung, "Multiterminal source coding," Ph.D. dissertation, School of Electrical Engineering, Cornell University, Ithaca, NY, May 1978.
- [14] H. Viswanathan and T. Berger, "The quadratic Gaussian CEO problem," *IEEE Trans. Inform. Theory*, vol. 43, pp. 1549-1559, Sept. 1997.
- [15] H. Yamamoto and K. Itoh, "Source coding theory for multiterminal communication systems with a remote source", *Trans. of the IECE of Japan*, vol. E63, no.10, pp. 700-706, Oct. 1980.
- [16] T. J. Flynn and R. M. Gray, "Encoding of correlated observations," *IEEE Trans. Inform. Theory*, vol. IT-33, pp. 773-787, Nov. 1987.